

Linear-Quadratic Mean Field Stackelberg Stochastic Differential Game with Partial Information and Common Noise ^{*}

Yu Si[†], Jingtao Shi[‡]

May 7, 2024

Abstract: This paper is concerned with a linear-quadratic mean field Stackelberg stochastic differential game with partial information and common noise, which contains a leader and a large number of followers. To be specific, the followers face a large population Nash game after the leader first announces his strategy, while the leader will then optimize his own cost functional on consideration of the followers' reactions. The state equation of the leader and followers are both general stochastic differential equations, where the diffusion terms contain both the control and state variables. However, the followers' average state terms enter into the drift term of the leader's state equation, reflecting that the leader's state is influenced by the followers' states. By virtue of stochastic maximum principle with partial information and optimal filter technique, we deduce the open-loop adapted decentralized strategies and feedback decentralized strategies of this leader-followers system, and demonstrate that the decentralized strategies are the corresponding ε -Stackelberg-Nash equilibrium.

Keywords: Stackelberg stochastic differential game, mean field games, partial information, common noise, state-estimate feedback Stackelberg-Nash equilibrium, optimal filtering, system of coupled Riccati equations

Mathematics Subject Classification: 93E20, 60H10, 49K45, 49N70, 91A23

^{*}This work is supported by National Key R&D Program of China (2022YFA1006104), National Natural Science Foundations of China (11971266, 12271304, 11831010), and Shandong Provincial Natural Science Foundations (ZR2022JQ01, ZR2020ZD24, ZR2019ZD42)

[†]*School of Mathematics, Shandong University, Jinan 250100, P.R. China, E-mail: 202112003@mail.sdu.edu.cn*

[‡]*Corresponding author. School of Mathematics, Shandong University, Jinan 250100, P.R. China, E-mail: shijingtao@sdu.edu.cn*

1 Introduction

Recently, the study of dynamic optimization in stochastic large-population systems has garnered significant attention. Distinguishing it from a standalone system, a large-population system comprises numerous agents, widely applied in fields such as engineering, finance and social science. In this context, the impact of a single agent is minimal and negligible, whereas the collective behaviors of the entire population are significant. All the agents are weakly coupled via the state average or empirical distribution in dynamics and cost functionals. Consequently, centralized strategies for a given agent, relying on information from all peers, are impractical. Instead, an effective strategy is to investigate the associated *mean-field games* (MFGs) to identify an approximate equilibrium by analyzing its limiting behavior. Along this research direction, we can obtain the decentralized strategies through the limiting auxiliary control problems and the related *consistency condition* (CC) system. The methodological foundations of MFGs, initially proposed by Lasry and Lions [21] and independently by Huang et al. [16, 17], have proven effective and tractable for analyzing weakly coupled stochastic controlled systems with mean field interactions, establishing approximate Nash equilibria. The interested readers can refer to [2, 8, 10, 11, 20, 27, 39] for *linear-quadratic* (LQ) MFGs, and refer to [4, 5, 6, 7, 15, 29] for further analysis of MFGs and related topics.

We mention that the above listed literature mainly focused on the case in which agents have access to full information. However, in the real world, usually agents can only get partial information at most cases. Huang and Wang [13] studied a class of dynamic optimization problems for a large-population system with partial information. Huang et al. [14] investigated a backward large-population system with partial information with full and partial information. Wang et al. [38] studied the optimal control problems for *forward-backward stochastic differential equations* (FBSDEs) with incomplete information thoroughly. Şen and Caines [34, 35] investigated the MFG problems with partial observation. Bensoussan et al. [3] focused on a class of linear-quadratic-Gaussian (LQG) MFGs with partial observation and common noise. Huang et al. [18, 19] studied a forward-backward stochastic system MFG with partial observation and common noise and a backward stochastic system MFG with partial information and common noise, respectively. Li et al. [23] investigated a large-population problem with partial information. Readers can see [22, 37] and the references therein for further studies.

The Stackelberg differential game, also known as the leader-follower differential game, arises in markets where certain companies possess greater authority to dominate others or individual entities. von Stackelberg [33] introduced the concept of the hierarchical solution. Yong [40] delved into a generalized framework of LQ stochastic leader-follower differential games. Nourian et al. [30] studied a large-population LQ leader-follower stochastic multi-agent systems and established their $(\varepsilon_1, \varepsilon_2)$ -Stackelberg-Nash equilibrium. Moon and Başar in [28] investigated continuous-time mean field LQ Stackelberg stochastic differential games by the fixed-point

method. Si and Wu [31] explored a backward-forward LQ Stackelberg MFG, where the leader's state equation is backward, and the follower's state equation is forward. Feng and Wang [9] investigated an LQ social optimal problem with a leader and a amount of followers. Wang [36] employed a direct method to solve LQ Stackelberg MFGs with a leader and a substantial number of followers.

In this paper, we consider a new class of LQ mean field Stackelberg stochastic differential games with partial information and common noise, which contains a leader and a number of followers. The leader first announces his strategy and then each follower optimizes its own cost based on the leader's announcement. At last, the leader chooses his own optimal strategy based on the responses of the followers. Compared with the existing literatures, the contributions of this paper are listed as follows.

- We introduced a general Stackelberg stochastic differential game with partial information and common noise. The common noise can not be observed by all agents, which force us to introduce a stochastic process as the frozen term, rather than a deterministic function, in the MFG analysis. Due to the framework of partial information, we need to use stochastic maximum principle with partial information and optimal filter technique to get the open loop decentralized optimal strategy and feedback decentralized optimal strategy of the auxiliary limiting problem.
- The state equation and cost functional of the leader both contain the state average term. This is motivated by real-world scenarios where all followers may have instantaneous and significant effects on the leader's dynamic. In addition, the state of the leader enters the cost functional of the followers, which means that changes in the leader can have an impact on the followers' evaluation criteria. This is consistent with the background where the leaders hold a dominant position. Therefore, complexity arises from the mean-field coupling term and highlight the strong coupling and interactivity among the state equations and cost functionals.
- The diffusion terms of all agents' state equations contain both the control and state variables, which makes the Hamiltonian system more complicated. And we apply decoupling technique to obtain the solvability of Hamiltonian system.
- Due to the application of dimension-extension techniques, the Riccati equations are asymmetric and complex, making their solvability quite challenging.

The rest of this paper is organized as follows. In Section 2, we formulate our problem. In Section 3, we introduce the auxiliary limiting problem and solve the problem of the followers and the leader in turn and derive the decentralized optimal strategies. In Section 4, we prove the decentralized optimal strategies are the ε -Stackelberg-Nash equilibria of the games. Finally, the conclusion is given in Section 5.

2 Problem formulation

Firstly, we introduce some notations that will be used throughout the paper. We consider a finite time interval $[0, T]$ for a fixed $T > 0$. Let $(\Omega, \mathcal{F}, \{\mathcal{F}_t\}_{t \geq 0}, \mathbb{P})$ be a complete filtered probability space, on which a standard $(N+1)$ -dimensional Brownian motion $\{W(s), W_i(s), 1 \leq i \leq N\}_{0 \leq s \leq t}$ is defined. $\{\mathcal{F}_t\}$ is defined as the complete information of the system at time t . Then, for any $t \geq 0$, we have

$$\mathcal{F}_t := \sigma \{W_i(s), W_0(s), W(s), 1 \leq i \leq N, 0 \leq s \leq t\} \vee \mathcal{N}_{\mathbb{P}},$$

where $\mathcal{N}_{\mathbb{P}}$ is the class of all \mathbb{P} -null sets. Define the available information of the i -th follower \mathcal{A}_i as

$$\mathcal{F}_t^{W_i} := \sigma \{W_i(s), 0 \leq s \leq t\} \vee \mathcal{N}_{\mathbb{P}},$$

and the available information of the leader \mathcal{A}_0 as

$$\mathcal{F}_t^{W_0} := \sigma \{W_0(s), 0 \leq s \leq t\} \vee \mathcal{N}_{\mathbb{P}}.$$

For $i = 0, 1, \dots, N$, define the involved information of \mathcal{A}_i as

$$\mathcal{F}_t^{W, W_i} := \sigma \{W(s), W_i(s), 0 \leq s \leq t\} \vee \mathcal{N}_{\mathbb{P}},$$

and let the information that is not observable by everyone (common noise) as

$$\mathcal{F}_t^W := \sigma \{W(s), 0 \leq s \leq t\} \vee \mathcal{N}_{\mathbb{P}}.$$

And define

$$\begin{aligned} \mathcal{G}_t^l &:= \sigma \{W_i(s), 0 \leq s \leq t, 0 \leq i \leq N\} \vee \mathcal{N}_{\mathbb{P}}, \\ \mathcal{G}_t^f &:= \sigma \{W_i(s), 0 \leq s \leq t, 1 \leq i \leq N\} \vee \mathcal{N}_{\mathbb{P}}, \\ \mathcal{F}_t^i &:= \sigma \{W(s), W_0(s), W_i(s), 0 \leq s \leq t\} \vee \mathcal{N}_{\mathbb{P}}, \quad \text{for } i = 1, \dots, N. \end{aligned}$$

Let \mathbb{R}^n be an n -dimensional Euclidean space with norm and inner product being defined as $|\cdot|$ and $\langle \cdot, \cdot \rangle$, respectively. Next, we introduce three spaces. A bounded, measurable function $f(\cdot) : [0, T] \rightarrow \mathbb{R}^n$ is denoted as $f(\cdot) \in L^\infty(0, T; \mathbb{R}^n)$. An \mathbb{R}^n -valued, \mathbb{F} -adapted stochastic process $f(\cdot) : \Omega \times [0, T] \rightarrow \mathbb{R}^n$ satisfying $\mathbb{E} \int_0^T |f(t)|^2 dt < \infty$ is denoted as $f(\cdot) \in L_{\mathbb{F}}^2(0, T; \mathbb{R}^n)$. Similarly, an \mathbb{R}^n -valued, \mathcal{F}_T -measurable random variable ξ with $\mathbb{E}\xi^2 < \infty$ is denoted as $\xi \in L_{\mathcal{F}_T}^2(\Omega, \mathbb{R}^n)$.

For any random variable or stochastic process X and filtration \mathcal{H} , $\mathbb{E}X$ and $\mathbb{E}[X|\mathcal{H}]$ represent the mathematical expectation and conditional mathematical expectation of X , respectively. For a given vector or matrix M , let M^\top represent its transpose. We denote the set of symmetric $n \times n$ matrices (resp. positive semi-definite matrices) with real elements by \mathcal{S}^n (resp. \mathcal{S}_+^n). If $M \in \mathcal{S}^n$ is positive (semi) definite, we abbreviate it as $M > (\geq) 0$. For a positive constant k , if $M \in \mathcal{S}^n$ and $M > kI$, we label it as $M \gg 0$.

Now, let us focus on a comprehensive population system comprised of $N + 1$ individual agents, denoted as $\{\mathcal{A}_i\}_{0 \leq i \leq N}$. The state $x_0(\cdot) \in \mathbb{R}$ of the leader \mathcal{A}_0 is given by the following linear SDE

$$\begin{cases} dx_0(t) = \left[A_0 x_0(t) + B_0 u_0(t) + E_0 x^{(N)}(t) + b_0 \right] dt \\ \quad + \left[C_0 x_0(t) + D_0 u_0(t) + F_0 x^{(N)}(t) + \sigma_0 \right] dW_0(t) \\ \quad + \left[\tilde{C}_0 x_0(t) + \tilde{D}_0 u_0(t) + \tilde{F}_0 x^{(N)}(t) + \tilde{\sigma}_0 \right] dW(t), \\ x_0(0) = \xi_0, \end{cases} \quad (2.1)$$

where $\xi_0 \in \mathbb{R}$ represents the initial state, and $x^{(N)}(\cdot) := \frac{1}{N} \sum_{i=1}^N x_i(\cdot)$ signifies the average state of the followers. The corresponding coefficients $A_0(\cdot)$, $B_0(\cdot)$, $C_0(\cdot)$, $D_0(\cdot)$, $E_0(\cdot)$, $F_0(\cdot)$, $\tilde{C}_0(\cdot)$, $\tilde{D}_0(\cdot)$, $\tilde{F}_0(\cdot)$, $b_0(\cdot)$, $\sigma_0(\cdot)$, $\tilde{\sigma}_0(\cdot)$ are deterministic \mathbb{R} -valued functions.

The state $x_i(\cdot)$ of the follower \mathcal{A}_i is given by the following linear SDE

$$\begin{cases} dx_i(t) = \left[A_1 x_i(t) + B_1 u_i(t) + E_1 x^{(N)}(t) + b_1 \right] dt \\ \quad + \left[C_1 x_i(t) + D_1 u_i(t) + F_1 x^{(N)}(t) + \sigma_1 \right] dW_i(t) \\ \quad + \left[\tilde{C}_1 x_i(t) + \tilde{D}_1 u_i(t) + \tilde{F}_1 x^{(N)}(t) + \tilde{\sigma}_1 \right] dW(t), \\ x_i(0) = \xi, \end{cases} \quad (2.2)$$

where $\xi \in \mathbb{R}$ represents the initial state, the coefficients $A_1(\cdot)$, $B_1(\cdot)$, $C_1(\cdot)$, $D_1(\cdot)$, $E_1(\cdot)$, $F_1(\cdot)$, $\tilde{C}_1(\cdot)$, $\tilde{D}_1(\cdot)$, $\tilde{F}_1(\cdot)$, $b_1(\cdot)$, $\sigma_1(\cdot)$, $\tilde{\sigma}_1(\cdot)$ are deterministic \mathbb{R} -valued functions.

The decentralized admissible control set $\mathcal{U}_0^{l,d}$ of the leader \mathcal{A}_0 is defined as

$$\mathcal{U}_0^{l,d} := \left\{ u_0(\cdot) \mid u_0(\cdot) \in L_{\mathcal{F}_t^{W_0}}^2(0, T; \mathbb{R}) \right\},$$

and the admissible centralized control set $\mathcal{U}_0^{l,c}$ of the leader \mathcal{A}_0 is defined as

$$\mathcal{U}_0^{l,c} := \left\{ u_0(\cdot) \mid u_0(\cdot) \in L_{\mathcal{G}_t^l}^2(0, T; \mathbb{R}) \right\}.$$

For $i = 1, \dots, N$, the decentralized admissible control set $\mathcal{U}_i^{f,d}$ of the i -th follower \mathcal{A}_i is defined as

$$\mathcal{U}_i^{f,d} := \left\{ u_i(\cdot) \mid u_i(\cdot) \in L_{\mathcal{F}_t^{W_i}}^2(0, T; \mathbb{R}) \right\},$$

and the centralized admissible control set $\mathcal{U}_i^{f,c}$ of the i -th follower \mathcal{A}_i is defined as

$$\mathcal{U}_i^{f,c} := \left\{ u_i(\cdot) \mid u_i(\cdot) \in L_{\mathcal{G}_t^f}^2(0, T; \mathbb{R}) \right\}.$$

For the leader \mathcal{A}_0 , the cost functional is defined by

$$\mathcal{J}_0(u_0(\cdot)) = \frac{1}{2} \mathbb{E} \int_0^T \left[R_0(t) u_0^2(t) + Q_0(t) \left(x_0(t) - x^{(N)}(t) \right)^2 \right] dt + G_0 x_0(T)^2, \quad (2.3)$$

where $Q_0(\cdot)$, $R_0(\cdot)$ are deterministic functions and G_0 is a constant. Let $u(\cdot) \equiv (u_1(\cdot), \dots, u_N(\cdot))$ be the set of control strategies of all followers and $u_{-i}(\cdot) \equiv (u_1(\cdot), \dots, u_{i-1}(\cdot), u_{i+1}(\cdot), \dots, u_N(\cdot))$ be the set of control strategies except for i -th follower \mathcal{A}_i . For $i = 1, \dots, N$, the cost functional of the i -th follower \mathcal{A}_i is defined by

$$\mathcal{J}_i(u_i(\cdot), u_{-i}(\cdot)) = \frac{1}{2} \mathbb{E} \left\{ \int_0^T \left[R_1(t) u_i^2(t) + Q_1(t) \left[x_i(t) - \left(\lambda x_0(t) + (1 - \lambda) x^{(N)}(t) \right) \right]^2 \right] dt + G_1 x_i(T)^2 \right\}, \quad (2.4)$$

where $Q_1(\cdot)$, $R_1(\cdot)$ are deterministic functions and G_1 is a constant. Here $\lambda \in [0, 1]$ is a constant.

Moreover, we introduce the following assumptions of coefficients.

Assumption 2.1. $A_0(\cdot), B_0(\cdot), E_0(\cdot), C_0(\cdot), D_0(\cdot), F_0(\cdot), \tilde{C}_0(\cdot), \tilde{D}_0(\cdot), \tilde{F}_0(\cdot), A_1(\cdot), B_1(\cdot), E_1(\cdot), C_1(\cdot), D_1(\cdot), F_1(\cdot), \tilde{C}_1(\cdot), \tilde{D}_1(\cdot), \tilde{F}_1(\cdot), b_0(\cdot), \sigma_0(\cdot), \tilde{\sigma}_0(\cdot), b_1(\cdot), \sigma_1(\cdot), \tilde{\sigma}_1(\cdot) \in L^\infty(0, T; \mathbb{R})$.

Assumption 2.2. $Q_0(\cdot), Q_1(\cdot), R_0(\cdot), R_1(\cdot) \in L^\infty(0, T; \mathbb{R})$, $Q_0(\cdot), Q_1(\cdot) \geq 0$, $R_0(\cdot), R_1(\cdot) \gg 0$; $G_0(\cdot), G_1(\cdot) \in \mathbb{R}$, $G_0(\cdot), G_1(\cdot) \geq 0$.

We mention that under assumption 2.1, the system of SDEs (2.1), (2.2) admits a unique solution $(x_0(\cdot), x_1(\cdot), \dots, x_N(\cdot)) \in L^2_{\mathcal{F}_t}(0, T; \mathbb{R}^{1+N})$. Under assumption 2.2, the cost functionals (2.3), (2.4) are well-defined.

Our *LQ mean field Stackelberg stochastic differential game with partial information and common noise*, investigated in this paper, can be stated as follows.

Problem 2.1. *Finding a set of strategies $(u_0^*(\cdot), u_1^*(\cdot), \dots, u_N^*(\cdot))$ satisfying the following conditions:*

(i) *given $u_0(\cdot) \in \mathcal{U}_0^{l,c}$, for $1 \leq i \leq N$, finding the control strategy set $u^*(\cdot; u_0) \equiv (u_1^*(\cdot; u_0), \dots, u_N^*(\cdot; u_0))$ of the followers $\mathcal{A}_1, \dots, \mathcal{A}_N$, such that*

$$\mathcal{J}_i(u_i^*(\cdot; u_0), u_{-i}^*(\cdot; u_0)) = \inf_{u_i(\cdot; u_0) \in \mathcal{U}_i^{f,c}} \mathcal{J}_i(u_i(\cdot), u_{-i}^*(\cdot; u_0));$$

(ii) *finding the control strategy $u_0^*(\cdot; u^*)$ of the leader \mathcal{A}_0 such that*

$$\mathcal{J}_0(u_0^*(\cdot; u^*)) = \inf_{u_0(\cdot; u^*) \in \mathcal{U}_0^{l,c}} \mathcal{J}_0(u_0(\cdot; u^*)).$$

We call $(u_0^*(\cdot), u_1^*(\cdot), \dots, u_N^*(\cdot))$ the *Stackelberg-Nash equilibrium* of Problem 2.1. Moreover, the corresponding state $(x_0^*(\cdot), x_1^*(\cdot), \dots, x_N^*(\cdot))$ is called the *optimal centralized trajectory*.

3 Limiting Stackelberg-Nash equilibria

Since the intricate nature arising from the coupling of the state-average $x^{(N)}(\cdot) := \frac{1}{N} \sum_{i=1}^N x_i(\cdot)$, Problem 2.1 becomes challenging to investigate. We shall employ the MFG theory to seek an approximate Stackelberg-Nash equilibrium, which serves as a bridge between the ‘‘centralized’’ LQ

games and the limiting state-average as the number of agents N approaches infinity. Typically, the state-average is replaced by its frozen limit term for computational convenience.

As $N \rightarrow +\infty$, let us assume that the state-average $x^{(N)}(\cdot)$ can be approximated by some \mathcal{F}_t^W -adapted processes $z(\cdot)$ that will be subsequently determined through a CC system. For the leader \mathcal{A}_0 , we introduce the following auxiliary state $\bar{x}_0(\cdot) \in L^2_{\mathcal{F}_t^{W, w_0}}(0, T; \mathbb{R})$ which satisfies the following linear SDE

$$\begin{cases} d\bar{x}_0(t) = [A_0(t)\bar{x}_0(t) + B_0(t)u_0(t) + E_0(t)z(t) + b_0(t)] dt \\ \quad + [C_0(t)\bar{x}_0(t) + D_0(t)u_0(t) + F_0(t)z(t) + \sigma_0(t)] dW_0(t) \\ \quad + [\tilde{C}_0(t)\bar{x}_0(t) + \tilde{D}_0(t)u_0(t) + \tilde{F}_0(t)z(t) + \tilde{\sigma}_0(t)] dW(t), \\ \bar{x}_0(0) = \xi_0, \end{cases} \quad (3.1)$$

and the limiting cost functional

$$J_0(u_0(\cdot)) = \frac{1}{2} \mathbb{E} \int_0^T [R_0(t)u_0(t)^2 + Q_0(t)(\bar{x}_0(t) - z(t))^2] dt + G_0\bar{x}_0^2(T). \quad (3.2)$$

For each follower \mathcal{A}_i , $i = 1, 2, \dots, N$, we introduce the following auxiliary state $\bar{x}_i(\cdot) \in L^2_{\mathcal{F}_t^{W, w_i}}(0, T; \mathbb{R})$ which satisfies the following linear SDE

$$\begin{cases} d\bar{x}_i(t) = [A_1(t)\bar{x}_i(t) + B_1(t)u_i(t) + E_1(t)z(t) + b_1(t)] dt \\ \quad + [C_1(t)\bar{x}_i(t) + D_1(t)u_i(t) + F_1(t)z(t) + \sigma_1(t)] dW_i(t) \\ \quad + [\tilde{C}_1(t)\bar{x}_i(t) + \tilde{D}_1(t)u_i(t) + \tilde{F}_1(t)z(t) + \tilde{\sigma}_1(t)] dW(t), \\ \bar{x}_i(0) = \xi, \end{cases} \quad (3.3)$$

and the limiting cost functional

$$J_i(u_i(\cdot)) = \frac{1}{2} \mathbb{E} \int_0^T [R_1(t)u_i^2(t) + Q_1(t)[\bar{x}_i(t) - (\lambda\bar{x}_0(t) + (1-\lambda)z(t))]^2] dt + G_1\bar{x}_i^2(T). \quad (3.4)$$

Subsequently, we propose the corresponding limiting Stackelberg-Nash stochastic differential game with partial information.

Problem 3.1. *Finding a set of strategies $(u_0^*(\cdot), u_1^*(\cdot), \dots, u_N^*(\cdot))$ satisfying the following conditions:*

(i) *Given $u_0(\cdot) \in \mathcal{U}_0^{l,d}$, for $1 \leq i \leq N$, finding the control strategy set $u^*(\cdot; u_0) = (u_1^*(\cdot; u_0), \dots, u_N^*(\cdot; u_0))$ of the followers $\mathcal{A}_1, \dots, \mathcal{A}_N$, such that*

$$J_i(u_i^*(\cdot; u_0), u_{-i}^*(\cdot; u_0)) = \inf_{u_i(\cdot) \in \mathcal{U}_i^{f,d}} J_i(u_i(\cdot; u_0), u_{-i}^*(\cdot; u_0));$$

(ii) *finding the control strategy $u_0^*(\cdot; u^*(\cdot))$ of the leader \mathcal{A}_0 such that*

$$J_0(u_0^*(\cdot; u^*)) = \inf_{u_0(\cdot; u^*) \in \mathcal{U}_0^{l,d}} J_0(u_0(\cdot; u^*)).$$

The above $(u_0^*(\cdot), u_1^*(\cdot), \dots, u_N^*(\cdot))$ is called the *decentralized Stackelberg-Nash equilibrium* of Problem 3.1.

3.1 Open-loop decentralized strategies of the followers

Observing that the frozen limiting state-average simplifies Problem 2.1 into essentially an LQ Stackelberg-Nash stochastic differential game with partial information, we will utilize the stochastic maximum principle with partial information to derive its Stackelberg-Nash equilibria. In the remainder of this section, for brevity and without causing ambiguity, we omit the time dependency of some functions and stochastic processes, except for the terminal time.

For $i = 1, \dots, N$, we define the Hamiltonian function $H_i : [0, T] \times \mathbb{R} \times \mathbb{R} \times \mathbb{R} \times \mathbb{R} \times \mathbb{R} \times \mathbb{R} \rightarrow \mathbb{R}$ of the i -th follower \mathcal{A}_i as

$$\begin{aligned} H_i(t, p_i, q_i, \tilde{q}_i, \bar{x}_i, \bar{x}_0, u_i) \\ := p_i [A_1 \bar{x}_i + B_1 u_i + E_1 z + b_1] + q_i [C_1 \bar{x}_i + D_1 u_i + F_1 z + \sigma_1] \\ + \tilde{q}_i \left[\tilde{C}_1 \bar{x}_i + \tilde{D}_1 u_i + \tilde{F}_1 z + \tilde{\sigma}_1 \right] - \frac{1}{2} \left[R_1 u_i^2 + Q_1 [\bar{x}_i - (\lambda \bar{x}_0 + (1 - \lambda)z)]^2 \right], \end{aligned} \quad (3.5)$$

and introduce the following adjoint equation

$$\begin{cases} dp_i = - \left[A_1 p_i + C_1 q_i + \tilde{C}_1 \tilde{q}_i - Q_1 [\bar{x}_i^* - (\lambda \bar{x}_0 + (1 - \lambda)z)] \right] dt \\ \quad + q_i dW_i + \tilde{q}_i dW + q_{i,0} dW_0, \\ p_i(T) = - G_i \bar{x}_i^*(T), \end{cases} \quad (3.6)$$

where the solution $(p_i(\cdot), q_i(\cdot), \tilde{q}_i(\cdot), q_{i,0}(\cdot))$ to the *backward SDE* (BSDE) (3.6) belongs to the space $L_{\mathcal{F}^i}^2(0, T; \mathbb{R}) \times L_{\mathcal{F}^i}^2(0, T; \mathbb{R}) \times L_{\mathcal{F}^i}^2(0, T; \mathbb{R})$, $\bar{x}_i^*(\cdot) \in L_{\mathcal{F}^i}^2(0, T; \mathbb{R})$ is the optimal solution to (3.3) of the follower \mathcal{A}_i , and $\bar{x}_0(\cdot) \in L_{\mathcal{F}_t^{W, W_0}}^2(0, T; \mathbb{R})$ is the solution to (3.1). By applying the stochastic maximum principle with partial information (for example, Theorem 3.1 of Bagheri and Øksendal [1], or Proposition 2.1 of Shi et al. [32]), we can obtain the open-loop decentralized optimal strategies for the subproblem (i) of Problem 3.1.

Theorem 3.1. *Let assumptions 2.1 and 2.2 hold. For given $u_0(\cdot) \in \mathcal{U}_0^{l,d}$ and $\bar{x}_0(\cdot) \in L_{\mathcal{F}_t^{W, W_0}}^2(0, T; \mathbb{R})$ be the solution to (3.1), then for $i = 1, \dots, N$, the open-loop decentralized optimal strategy of i -th follower \mathcal{A}_i is given by*

$$u_i^* = R_1^{-1} \left(B_1 \hat{p}_i + D_1 \hat{q}_i + \tilde{D}_1 \tilde{\hat{q}}_i \right), \quad \mathbb{P}\text{-a.s., a.e.}, \quad (3.7)$$

where $(\bar{x}_i^*(\cdot), p_i(\cdot), q_i(\cdot), \tilde{q}_i(\cdot), q_{i,0}(\cdot)) \in L_{\mathcal{F}_t^{W, W_i}}^2(0, T; \mathbb{R}) \times L_{\mathcal{F}^i}^2(0, T; \mathbb{R}) \times L_{\mathcal{F}^i}^2(0, T; \mathbb{R}) \times L_{\mathcal{F}^i}^2(0, T; \mathbb{R})$

satisfies the following stochastic Hamiltonian system

$$\left\{ \begin{array}{l} d\bar{x}_i^* = \left[A_1 \bar{x}_i^* + R_1^{-1} B_1^2 \hat{p}_i + R_1^{-1} B_1 D_1 \hat{q}_i + R_1^{-1} B_1 \tilde{D}_1 \tilde{q}_i + E_1 z + b_1 \right] dt \\ \quad + \left[C_1 \bar{x}_i^* + R_1^{-1} D_1 B_1 \hat{p}_i + R_1^{-1} D_1^2 \hat{q}_i + R_1^{-1} D_1 \tilde{D}_1 \tilde{q}_i + F_1 z + \sigma_1 \right] dW_i \\ \quad + \left[\tilde{C}_1 \bar{x}_i^* + R_1^{-1} \tilde{D}_1 B_1 \hat{p}_i + R_1^{-1} D_1 \tilde{D}_1 \hat{q}_i + R_1^{-1} \tilde{D}_1^2 \tilde{q}_i + \tilde{F}_1 z + \tilde{\sigma}_1 \right] dW, \\ dp_i = - \left[A_1 p_i + C_1 q_i + \tilde{C}_1 \tilde{q}_i - Q_1 [\bar{x}_i^* - (\lambda \bar{x}_0 + (1 - \lambda) z)] \right] dt \\ \quad + q_i dW_i + \tilde{q}_i dW + q_{i,0} dW_0, \\ \bar{x}_i^*(0) = \xi, \quad p_i(T) = -G_1 \bar{x}_i^*(T), \end{array} \right. \quad (3.8)$$

where we denote $\hat{p}_i := \mathbb{E} \left[p_i | \mathcal{F}_t^{W_i} \right]$, etc., with $z(\cdot) \in L_{\mathcal{F}_t^W}^2(0, T; \mathbb{R})$ to be determined.

Proof. For each $i = 1, \dots, N$, for the open-loop decentralized optimal strategy $u_i^*(\cdot)$, assuming $\bar{x}_i^*(\cdot)$ represents the corresponding state trajectory, and $(p_i(\cdot), q_i(\cdot), \tilde{q}_i(\cdot), q_{i,0}(\cdot))$ is the unique solution to the second equation in (3.8) relative to $(\bar{x}_i^*(\cdot), u_i^*(\cdot))$, the stochastic maximum principle with partial information can be expressed in the following form

$$\mathbb{E} \left[\frac{\partial H_i}{\partial u_i} (t, p_i, q_i, \tilde{q}_i, \bar{x}_i, u_i) (u_i - u_i^*) \middle| \mathcal{F}_t^{W_i} \right] = 0, \quad \text{for any } u_i(\cdot) \in \mathbb{R}, \mathbb{P}\text{-a.s., a.e..}$$

Substituting (3.5) into it, we can derive that

$$\mathbb{E} \left[\left(B_1 p_i + D_1 q_i + \tilde{D}_1 \tilde{q}_i - R_1 u_i^* \right) (u_i - u_i^*) \middle| \mathcal{F}_t^{W_i} \right] = 0, \quad \text{for any } u_i \in \mathbb{R}, \mathbb{P}\text{-a.s., a.e..}$$

Then we can derive that

$$u_i^* = R^{-1} \left(B_1 \hat{p}_i + D_1 \hat{q}_i + \tilde{D}_1 \tilde{q}_i \right), \quad \mathbb{P}\text{-a.s., a.e..}$$

The proof is complete. \square

Moreover, because the cost functional (3.4) of Problem 3.1 (i) is strictly convex, it allows a unique optimal control, so the sufficiency of the optimal control (3.7) can also be obtained. In addition, the state feedback representation of (3.7) can be obtained by Riccati equations.

Next, we will study the unknown frozen limiting state-average $z(\cdot)$, which is an \mathcal{F}_t^W -adapted process. When $N \rightarrow \infty$, we would like to approximate $x_i^*(\cdot)$ by $\bar{x}_i^*(\cdot)$, thus $\frac{1}{N} \sum_{i=1}^N x_i^*(\cdot)$ is approximated by $\frac{1}{N} \sum_{i=1}^N \bar{x}_i^*(\cdot)$. Since the \mathcal{F}_t^{W, W_i} -adapted process $\bar{x}_i^*(\cdot)$ and \mathcal{F}_t^{W, W^j} -adapted process $\bar{x}_j^*(\cdot)$ (for $1 \leq i \neq j \leq N$) are identically distributed and conditionally independent given $\mathbb{E} [\cdot | \mathcal{F}^W]$, we can apply the conditional strong law of large numbers (Majerek et al. [26]) to draw a conclusion

$$z(\cdot) = \lim_{N \rightarrow \infty} \frac{1}{N} \sum_{i=1}^N \bar{x}_i^*(\cdot) = \mathbb{E} [\bar{x}_i^*(\cdot) | \mathcal{F}^W]. \quad (3.9)$$

According to (3.3), by replacing $z(\cdot)$ by $\mathbb{E}[\bar{x}_i^*(\cdot) | \mathcal{F}_t^W]$, we can obtain for each $i = 1, \dots, N$,

$$\begin{cases} d\bar{x}_i^* = [A_1\bar{x}_i^* + B_1u_i^* + E_1\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + b_1] dt \\ \quad + [C_1\bar{x}_i^* + D_1u_i^* + F_1\mathbb{E}[\bar{x}_i^*(\cdot) | \mathcal{F}_t^W] + \sigma_1] dW_i \\ \quad + [\tilde{C}_1\bar{x}_i^* + \tilde{P}_1u_i^* + \tilde{F}_1\mathbb{E}[\bar{x}_i^*(\cdot) | \mathcal{F}_t^W] + \tilde{\sigma}_1] dW, \\ \bar{x}_i^*(0) = \xi. \end{cases} \quad (3.10)$$

Taking expectation on both sides of the equation (3.10), we have

$$\begin{cases} d\mathbb{E}\bar{x}_i^* = [(A_1 + E_1)\mathbb{E}\bar{x}_i^* + B_1\mathbb{E}u_i^* + b_1] dt, \\ \mathbb{E}\bar{x}_i^*(0) = \xi, \quad \text{for } i = 1, \dots, N. \end{cases} \quad (3.11)$$

Since $u_i^*(\cdot)$ is $\mathcal{F}_t^{W_i}$ -adapted, we can obtain $\mathbb{E}[u_i^* | \mathcal{F}_t^W] = \mathbb{E}[u_i^*]$, for $i = 1, \dots, N$. Then taking $\mathbb{E}[\cdot | \mathcal{F}_t^W]$ on both sides of (3.10), we get for $i = 1, \dots, N$,

$$\begin{cases} dz = [(A_1 + E_1)z + B_1\mathbb{E}u_i^* + b_1] dt + \left[(\tilde{C}_1 + \tilde{F}_1)z + \tilde{D}_1\mathbb{E}u_i^* + \tilde{\sigma}_1 \right] dW, \\ z(0) = \xi, \end{cases} \quad (3.12)$$

which admits a unique solution $z(\cdot) \in L^2_{\mathcal{F}_t^W}(0, T; \mathbb{R})$. This indicates that for $i = 1, \dots, N$,

$$\begin{cases} d\mathbb{E}z = [(A_1 + E_1)\mathbb{E}z + B_1\mathbb{E}u_i^* + b_1] dt, \\ \mathbb{E}z(0) = \xi. \end{cases} \quad (3.13)$$

That is to say, $\mathbb{E}\bar{x}_i^*(t) \equiv \mathbb{E}z(t), t \in [0, T]$, for $i = 1, \dots, N$.

According to (3.8), by replacing $z(\cdot)$ by $\mathbb{E}[\bar{x}_i^*(\cdot) | \mathcal{F}_t^W]$, we noticing the second equation of (3.8) is couple with the state of leader \mathcal{A}_0 , then we arrive at the following CC system, which is a *conditional mean field FBSDE* (CMF-FBSDE) of $(\bar{x}_i^*(\cdot), \bar{x}_0(\cdot), p_i(\cdot), q_i(\cdot), \tilde{q}_i(\cdot), q_{i,0}(\cdot)) \in L^2_{\mathcal{F}_t^{W, W_i}}(0, T; \mathbb{R}) \times L^2_{\mathcal{F}_t^{W, W_0}}(0, T; \mathbb{R}) \times L^2_{\mathcal{F}_t^i}(0, T; \mathbb{R}) \times L^2_{\mathcal{F}_t^i}(0, T; \mathbb{R}) \times L^2_{\mathcal{F}_t^i}(0, T; \mathbb{R})$ ([32]):

$$\begin{cases} d\bar{x}_i^* = \left[A_1\bar{x}_i^* + R_1^{-1}B_1^2\hat{p}_i + R_1^{-1}B_1D_1\hat{q}_i + R_1^{-1}B_1\tilde{D}_1\hat{\tilde{q}}_i + E_1\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + b_1 \right] dt \\ \quad + \left[C_1\bar{x}_i^* + R_1^{-1}D_1B_1\hat{p}_i + R_1^{-1}D_1^2\hat{q}_i + R_1^{-1}D_1\tilde{D}_1\hat{\tilde{q}}_i + F_1\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \sigma_1 \right] dW_i \\ \quad + \left[\tilde{C}_1\bar{x}_i^* + R_1^{-1}\tilde{D}_1B_1\hat{p}_i + R_1^{-1}D_1\tilde{D}_1\hat{q}_i + R_1^{-1}\tilde{D}_1^2\hat{\tilde{q}}_i + \tilde{F}_1\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \tilde{\sigma}_1 \right] dW, \\ d\bar{x}_0 = \left[A_0\bar{x}_0 + B_0u_0 + E_0\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + b_0 \right] dt \\ \quad + \left[C_0\bar{x}_0 + D_0u_0 + F_0\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \sigma_0 \right] dW_0 \\ \quad + \left[\tilde{C}_0\bar{x}_0 + \tilde{D}_0u_0 + \tilde{F}_0\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \tilde{\sigma}_0 \right] dW, \\ dp_i = - \left[A_1p_i + C_1q_i + \tilde{C}_1\tilde{q}_i - Q_1[\bar{x}_i^* - (\lambda\bar{x}_0 + (1-\lambda)\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W])] \right] dt \\ \quad + q_i dW_i + \tilde{q}_i dW + q_{i,0} dW_0, \\ \bar{x}_i^*(0) = \xi, \quad \bar{x}_0(0) = \xi_0, \quad p_i(T) = -G_1\bar{x}_i^*(T), \quad \text{for } i = 1, \dots, N. \end{cases} \quad (3.14)$$

Noting that (3.14) possesses a fully coupled structure and contains conditional expectation terms, we will discuss its well-posedness in the following subsection.

3.2 State feedback decentralized strategies of the followers

In this section, we derive the state feedback representation of the decentralized optimal strategies (3.7) of the followers, through Riccati equations.

Noting the terminal condition and structure of (3.14), for each $i = 1, \dots, N$, we suppose

$$p_i(t) = -P_1(t)\bar{x}_i^*(t) - P_2(t)\mathbb{E}[\bar{x}_i^*(t)] - \varphi_i(t), \quad t \in [0, T], \quad (3.15)$$

with $P_1(T) = G_1$, $P_2(T) = 0$ for two deterministic differentiable functions $P_1(\cdot)$, $P_2(\cdot)$, and with $\varphi_i(T) = 0$, for an \mathcal{F}_t^i -adapted process triple $(\varphi_i(\cdot), \xi_{i,0}(\cdot), \xi_i(\cdot))$ satisfying a BSDE

$$d\varphi_i(t) = \alpha_i(t)dt + \xi_{i,0}dW_0 + \xi_i dW_i,$$

where the \mathcal{F}_t^i -adapted process $\alpha_i(\cdot)$ is to be determined. Applying Itô's formula, we have

$$\begin{aligned} dp_i &= -P_1 d\bar{x}_i^* - \dot{P}_1 \bar{x}_i^* dt - P_2 d\mathbb{E}\bar{x}_i^* - \dot{P}_2 \mathbb{E}\bar{x}_i^* dt - \alpha_i dt - \xi_{i,0} dW_0 - \xi_i dW_i \\ &= -P_1 \left\{ [A_1 \bar{x}_i^* + B_1 u_i^* + E_1 \mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + b_1] dt + [C_1 \bar{x}_i^* + D_1 u_i^* + F_1 \mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] \right. \\ &\quad \left. + \sigma_1] dW_i + [\tilde{C}_1 \bar{x}_i^* + \tilde{D}_1 u_i^* + \tilde{F}_1 \mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \tilde{\sigma}_1] dW \right\} - \dot{P}_1 \bar{x}_i^* \\ &\quad - P_2 [(A_1 + E_1)\mathbb{E}\bar{x}_i^* + B_1 \mathbb{E}u_i^* + b_1] dt - \dot{P}_2 \mathbb{E}\bar{x}_i^* dt - \alpha_i(t)dt - \xi_{i,0} dW_0 - \xi_i dW_i \\ &= - \left[A_1 p_i + C_1 q_i + \tilde{C}_1 \tilde{q}_i - Q_1 [\bar{x}_i^* - (\lambda \bar{x}_0 + (1 - \lambda) \mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W])] \right] dt + q_i dW_i \\ &\quad + \tilde{q}_i dW + q_{i,0} dW_0, \quad \text{for } i = 1, \dots, N. \end{aligned}$$

By comparing the coefficients of the diffusion terms, we achieve

$$\begin{cases} q_i = -P_1 [C_1 \bar{x}_i^* + D_1 u_i^* + F_1 \mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \sigma_1] - \xi_i, \\ \tilde{q}_i = -P_1 [\tilde{C}_1 \bar{x}_i^* + \tilde{D}_1 u_i^* + \tilde{F}_1 \mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \tilde{\sigma}_1], \\ q_{i,0} = -\xi_{i,0}, \quad \mathbb{P}\text{-a.s., a.e., for } i = 1, \dots, N. \end{cases} \quad (3.16)$$

Then, taking the conditional expectation $\mathbb{E}[\cdot | \mathcal{F}_t^{W_i}]$, we can obtain

$$\begin{cases} \hat{p}_i = -P_1 \hat{x}_i^* - P_2 \mathbb{E}\bar{x}_i^* - \hat{\varphi}_i, \\ \hat{q}_i = -P_1 [C_1 \hat{x}_i^* + D_1 u_i^* + F_1 \mathbb{E}\bar{x}_i^* + \sigma_1] - \hat{\xi}_i, \\ \hat{\tilde{q}}_i = -P_1 [\tilde{C}_1 \hat{x}_i^* + \tilde{D}_1 u_i^* + \tilde{F}_1 \mathbb{E}\bar{x}_i^* + \tilde{\sigma}_1], \\ \hat{q}_{i,0} = -\hat{\xi}_{i,0}, \quad \text{for } i = 1, \dots, N. \end{cases} \quad (3.17)$$

Substituting them into (3.7), we have

$$\begin{aligned} u_i^* &= -\mathcal{R}_1^{-1} \left[\left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 \hat{x}_i^* + \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right) \mathbb{E}\bar{x}_i^* \right. \\ &\quad \left. + B_1 \hat{\varphi}_i + D_1 P_1 \sigma_1 + \tilde{D}_1 P_1 \tilde{\sigma}_1 - D_1 \hat{\xi}_i \right], \quad \mathbb{P}\text{-a.s., a.e., for } i = 1, \dots, N. \end{aligned} \quad (3.18)$$

with $\mathcal{R}_1 := R_1 + D_1^2 P_1 + \tilde{D}_1^2 P_1$, and

$$\begin{aligned} \mathbb{E}u_i^* = & -\mathcal{R}_1^{-1} \left\{ \left[\left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 + \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right) \right] \mathbb{E}\bar{x}_i^* \right. \\ & \left. + B_1 \mathbb{E}\varphi_i + \left(D_1 \sigma_1 + \tilde{D}_1 \tilde{\sigma}_1 \right) P_1 - D_1 \mathbb{E}\xi_i \right\}, \quad \text{for } i = 1, \dots, N. \end{aligned} \quad (3.19)$$

By compare the coefficients of the drift terms, we get for $i = 1, \dots, N$,

$$\begin{aligned} -\alpha_i = & \left(P_1 A_1 + A_1 P_1 + C_1^2 P_1 + \tilde{C}_1^2 P_1 + Q_1 + \dot{P}_1 \right) \bar{x}_i^* \\ & + \left(\dot{P}_2 + P_2 A_1 + P_2 E_1 + A_1 P_2 \right) \mathbb{E}\bar{x}_i^* \\ & + \left(P_1 E_1 + C_1 P_1 F_1 + \tilde{C}_1 P_1 \tilde{F}_1 - Q_1 (1 - \lambda) \right) \mathbb{E} \left[\bar{x}_i^* \mid \mathcal{F}_t^W \right] \\ & + \left(P_1 B_1 + C_1 P_1 D_1 + \tilde{C}_1 P_1 \tilde{D}_1 \right) u_i^* + P_2 B_1 \mathbb{E}u_i^* \\ & + P_1 b_1 + P_2 b_1 + A_1 \varphi_i + C_1 P_1 \sigma_1 + C_1 \xi_i + \tilde{C}_1 P_1 \tilde{\sigma}_1 - Q_1 \lambda \bar{x}_0. \end{aligned} \quad (3.20)$$

Then substitute (3.18) and (3.19) into (3.20), we obtain

$$\begin{aligned} -\alpha_i = & \left(\dot{P}_1 + (2A_1 + C_1^2 + \tilde{C}_1^2) P_1 + Q_1 \right) \bar{x}_i^* + \left(\dot{P}_2 + (2A_1 + E_1) P_2 \right) \mathbb{E}\bar{x}_i^* \\ & + \left(P_1 (E_1 + C_1 F_1 + \tilde{C}_1 \tilde{F}_1) - Q_1 (1 - \lambda) \right) \mathbb{E} \left[\bar{x}_i^* \mid \mathcal{F}_t^W \right] - \left(B_1 + C_1 D_1 + \tilde{C}_1 \tilde{D}_1 \right) P_1 \mathcal{R}_1^{-1} \\ & \left[\left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 \hat{x}_i^* + \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right) \mathbb{E}\bar{x}_i^* \right. \\ & \left. + B_1 \hat{\varphi}_i + D_1 P_1 \sigma_1 + \tilde{D}_1 P_1 \tilde{\sigma}_1 - D_1 \hat{\xi}_i \right] - P_2 B_1 \mathcal{R}_1^{-1} \left\{ \left[\left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 \right. \right. \\ & \left. \left. + B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right] \mathbb{E}\bar{x}_i^* + B_1 \mathbb{E}\varphi_i + \left(D_1 \sigma_1 + \tilde{D}_1 \tilde{\sigma}_1 \right) P_1 - D_1 \mathbb{E}\xi_i \right\} \\ & + P_1 b_1 + P_2 b_1 + A_1 \varphi_i + C_1 P_1 \sigma_1 + C_1 \xi_i + \tilde{C}_1 P_1 \tilde{\sigma}_1 - Q_1 \lambda \bar{x}_0, \quad \text{for } i = 1, \dots, N. \end{aligned}$$

Noting $\bar{x}_0(\cdot)$ is \mathcal{F}_t^{W, W_0} -adapted, we have $\mathbb{E} \left[\bar{x}_0 \mid \mathcal{F}_t^{W_i} \right] = \mathbb{E}\bar{x}_0$. Then take the conditional expectation $\mathbb{E} \left[\cdot \mid \mathcal{F}^{W_i} \right]$ on both sides of above equation, we can obtain

$$\begin{aligned} -\hat{\alpha}_i = & \left[\dot{P}_1 + \left(2A_1 + C_1^2 + \tilde{C}_1^2 \right) P_1 - \mathcal{R}_1^{-1} \left(B_1 + C_1 D_1 + \tilde{C}_1 \tilde{D}_1 \right)^2 P_1^2 + Q_1 \right] \hat{x}_i^* \\ & + \left\{ \dot{P}_2 + (2A_1 + E_1) P_2 + P_1 \left(E_1 + C_1 F_1 + \tilde{C}_1 \tilde{F}_1 \right) - Q_1 (1 - \lambda) \right. \\ & \left. - \left(B_1 + C_1 D_1 + \tilde{C}_1 \tilde{D}_1 \right) P_1 \mathcal{R}_1^{-1} \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right) \right. \\ & \left. - P_2 B_1 \mathcal{R}_1^{-1} \left[\left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 + B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right] \right\} \mathbb{E}\bar{x}_i^* \\ & - \left(B_1 + C_1 D_1 + \tilde{C}_1 \tilde{D}_1 \right) P_1 \mathcal{R}_1^{-1} \left(B_1 \hat{\varphi}_i + D_1 P_1 \sigma_1 + \tilde{D}_1 P_1 \tilde{\sigma}_1 - D_1 \hat{\xi}_i \right) \\ & - P_2 B_1 \mathcal{R}_1^{-1} \left[B_1 \mathbb{E}\varphi_i + \left(D_1 \sigma_1 + \tilde{D}_1 \tilde{\sigma}_1 \right) P_1 - D_1 \mathbb{E}\xi_i \right] \\ & + P_1 b_1 + P_2 b_1 + A_1 \hat{\varphi}_i + C_1 P_1 \sigma_1 + C_1 \xi_i + \tilde{C}_1 P_1 \tilde{\sigma}_1 - Q_1 \lambda \mathbb{E}\bar{x}_0, \quad \text{for } i = 1, \dots, N. \end{aligned}$$

Moreover, from (3.1), we get the following linear *ordinary differential equation* (ODE):

$$\begin{cases} d\mathbb{E}\bar{x}_0 = (A_0\mathbb{E}\bar{x}_0 + B_0\mathbb{E}u_0 + E_0\mathbb{E}z + b_0) dt, \\ \mathbb{E}\bar{x}_0(0) = \xi_0. \end{cases} \quad (3.21)$$

Thus, we introduce the Riccati equations as follows:

$$\begin{cases} \dot{P}_1 + \left(2A_1 + C_1^2 + \tilde{C}_1^2\right) P_1 - \mathcal{R}_1^{-1} \left(B_1 + C_1D_1 + \tilde{C}_1\tilde{D}_1\right)^2 P_1^2 + Q_1 = 0, \\ P_1(T) = G_1, \end{cases} \quad (3.22)$$

$$\begin{cases} \dot{P}_2 + P_2 \left[2A_1 + E_1 - 2 \left(B_1 + C_1D_1 + \tilde{C}_1\tilde{D}_1\right) P_1 \mathcal{R}_1^{-1} B_1 - \left(D_1F_1 + \tilde{D}_1\tilde{F}_1\right) B_1 P_1\right] \\ - B_1^2 \mathcal{R}_1^{-1} P_2^2 + P_1 \left(E_1 + C_1F_1 + \tilde{C}_1\tilde{F}_1\right) \\ - \left(B_1 + C_1D_1 + \tilde{C}_1\tilde{D}_1\right) P_1^2 \mathcal{R}_1^{-1} \left(D_1F_1 + \tilde{D}_1\tilde{F}_1\right) - Q_1(1 - \lambda) = 0, \\ P_2(T) = 0, \end{cases} \quad (3.23)$$

and the equation of $(\hat{\varphi}_i(\cdot), \hat{\xi}_i(\cdot)) \in L^2_{\mathcal{F}_t^{w_i}}(0, T; \mathbb{R}) \times L^2_{\mathcal{F}_t^{w_i}}(0, T; \mathbb{R})$ as

$$\begin{cases} d\hat{\varphi}_i = \left\{ \left(B_1 + C_1D_1 + \tilde{C}_1\tilde{D}_1\right) P_1 \mathcal{R}_1^{-1} \left(B_1\hat{\varphi}_i + D_1P_1\sigma_1 + \tilde{D}_1P_1\tilde{\sigma}_1\right) \right. \\ \quad \left. + P_2B_1\mathcal{R}_1^{-1} \left[B_1\mathbb{E}\varphi_i + \left(D_1\sigma_1 + \tilde{D}_1\tilde{\sigma}_1\right) P_1 - D_1\mathbb{E}\xi_i\right] \right. \\ \quad \left. - \left[P_1b_1 + P_2b_1 + A_1\hat{\varphi}_i + C_1P_1\sigma_1 + C_1\hat{\xi}_i + \tilde{C}_1P_1\tilde{\sigma}_1 - Q_1\lambda\mathbb{E}\bar{x}_0\right] \right\} dt + \hat{\xi}_i dW_i, \\ \hat{\varphi}_i(T) = 0, \quad \text{for } i = 1, \dots, N. \end{cases} \quad (3.24)$$

By the existence and uniqueness of the solution to mean-field type BSDEs (Li et al. [24]), in fact, (3.24) degenerates to the following linear *backward ODE* (BODE):

$$\begin{cases} d\mathbb{E}\varphi_i = (M_1\mathbb{E}\varphi_i + Q_1\lambda\mathbb{E}\bar{x}_0 + M_2) dt, \\ \mathbb{E}\varphi_i(T) = 0, \quad \text{for } i = 1, \dots, N, \end{cases} \quad (3.25)$$

which is coupled with the linear ODE (3.21), where we have denoted

$$\begin{cases} M_1 := \left(B_1 + C_1D_1 + \tilde{C}_1\tilde{D}_1\right) P_1 \mathcal{R}_1^{-1} B_1 - A_1 + P_2B_1\mathcal{R}_1^{-1} B_1, \\ M_2 := \left(B_1 + C_1D_1 + \tilde{C}_1\tilde{D}_1\right) P_1 \mathcal{R}_1^{-1} \left(D_1P_1\sigma_1 + \tilde{D}_1P_1\tilde{\sigma}_1\right) + P_2B_1\mathcal{R}_1^{-1} \left(D_1\sigma_1 + \tilde{D}_1\tilde{\sigma}_1\right) P_1 \\ - P_1b_1 - P_2b_1 - C_1P_1\sigma_1 - \tilde{C}_1P_1\tilde{\sigma}_1. \end{cases}$$

Noting (3.25) is independent of i , we could drop the subscript i in the rest part of this paper, that is, $\varphi_i(t) \equiv \varphi(t), t \in [0, T]$, for all $i = 1, \dots, N$. Therefore, we can get the following *forward-backward ODEs* (FBODEs):

$$\begin{cases} d\mathbb{E}z = (N_1\mathbb{E}z - B_1\mathcal{R}_1^{-1}B_1\mathbb{E}\varphi + N_2) dt, \\ d\mathbb{E}\bar{x}_0 = (A_0\mathbb{E}\bar{x}_0 + B_0\mathbb{E}u_0 + E_0\mathbb{E}z + b_0) dt, \\ d\mathbb{E}\varphi = (M_1\mathbb{E}\varphi + Q_1\lambda\mathbb{E}\bar{x}_0 + M_2) dt, \\ \mathbb{E}z(0) = \xi, \quad \mathbb{E}\bar{x}_0(0) = \xi_0, \quad \mathbb{E}\varphi(T) = 0, \end{cases} \quad (3.26)$$

where

$$\begin{cases} N_1 := A_1 + E_1 - B_1 \mathcal{R}_1^{-1} \left[(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1) P_1 + B_1 P_2 + D_1 F_1 P + \tilde{D}_1 \tilde{F}_1 P_1 \right], \\ N_2 := -B_1 \mathcal{R}_1^{-1} (D_1 \sigma_1 + \tilde{D}_1 \tilde{\sigma}_1) P_1 + b_1. \end{cases}$$

Now, we derive the solvability of the equations (3.22), (3.23) and (3.26). Firstly, we introduce

Assumption 3.1.

$$P_1 (E_1 + C_1 F_1 + \tilde{C}_1 \tilde{F}_1) - (B_1 + C_1 D_1 + \tilde{C}_1 \tilde{D}_1) P_1^2 \mathcal{R}_1^{-1} (D_1 F_1 + \tilde{D}_1 \tilde{F}_1) - Q_1 (1 - \lambda) \geq 0.$$

Under assumptions 2.1 and 2.2, (3.22) is standard Riccati equation. Noticing that (3.23) is a standard Riccati equation under assumption 3.1. Therefore, applying the standard results of Chapter 6 in Yong and Zhou [41], both (3.22) and (3.23) exist unique solutions.

Then, we derive the condition under which (3.26) is solvable. To this end, we first rewrite (3.26) in the following form:

$$\begin{cases} d \begin{pmatrix} \mathbb{E}z \\ \mathbb{E}\bar{x}_0 \\ \mathbb{E}\varphi \end{pmatrix} = \Pi \begin{pmatrix} \mathbb{E}z \\ \mathbb{E}\bar{x}_0 \\ \mathbb{E}\varphi \end{pmatrix} + \Delta, \\ \mathbb{E}z(0) = \xi, \quad \mathbb{E}\bar{x}_0(0) = \xi_0, \quad \mathbb{E}\varphi(T) = 0, \end{cases} \quad (3.27)$$

where

$$\Pi := \begin{pmatrix} N_1 & 0 & -B_1 \mathcal{R}_1^{-1} B_1 \\ E_0 & A_0 & 0 \\ 0 & Q_1 \lambda & M_1 \end{pmatrix}, \quad \Delta := \begin{pmatrix} N_2 \\ B_0 \mathbb{E}u_0 + b_0 \\ M_2 \end{pmatrix}.$$

Then, by the variation of constant formula, we have

$$\begin{pmatrix} \mathbb{E}z \\ \mathbb{E}\bar{x}_0 \\ \mathbb{E}\varphi \end{pmatrix} = \Theta(t) \begin{pmatrix} \xi \\ \xi_0 \\ \mu \end{pmatrix} + \Theta(t) \int_0^t \Theta^{-1}(s) \Delta ds$$

where $\Theta(\cdot)$ is the fundamental solution matrix of the ODE: $\dot{\Psi} = \Pi \Psi$ with the initial conditions $\Psi(0) = I_3$ and $\mathbb{E}\varphi$ need to satisfy the initial conditions $\mathbb{E}\varphi(0) = \mu$. Noting the terminal condition in (3.27), now we present the following result.

Proposition 3.1. *For given $T > 0$, assume*

$$\det \left[\begin{pmatrix} 0 & 0 & 1 \end{pmatrix} \Theta(T) \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix} \right] \neq 0,$$

then (3.26) has a unique solution on $[0, T]$, for any initial value ξ and ξ_0 .

Remark 3.1. Similar results about the solvability of coupled FBODE can be referred to the Chapter 2, Section 3 of Ma and Yong [25] and Section 4 of Huang and Huang [12].

Then, the state feedback representation of the decentralized optimal strategies of the followers can be obtained in the following theorem.

Theorem 3.2. Let assumptions 2.1, 2.2 and 3.1 hold, for given $u_0(\cdot) \in \mathcal{U}_0^{l,d}$, the state feedback optimal strategies of the followers $\mathcal{A}_i, i = 1, \dots, N$, can be represented as

$$u_i^* = -\mathcal{R}_1^{-1} \left[\left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 \hat{x}_i^* + \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right) \mathbb{E}z \right. \\ \left. + B_1 \mathbb{E}\varphi + D_1 P_1 \sigma_1 + \tilde{D}_1 P_1 \tilde{\sigma}_1 \right], \quad \mathbb{P}\text{-a.s., a.e.}, \quad (3.28)$$

where $\hat{x}_i^*(\cdot) \in L^2_{\mathcal{F}_t^{W_i}}(0, T; \mathbb{R})$ satisfies

$$\left\{ \begin{array}{l} d\hat{x}_i^* = \left\{ \left[A_1 - B_1 \mathcal{R}_1^{-1} \left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 \right] \hat{x}_i^* \right. \\ \quad + \left[E_1 - B_1 \mathcal{R}_1^{-1} \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right) \right] \mathbb{E}z - B_1 \mathcal{R}_1^{-1} B_1 \mathbb{E}\varphi \\ \quad \left. - B_1 \mathcal{R}_1^{-1} \left(D_1 P_1 \sigma_1 + \tilde{D}_1 P_1 \tilde{\sigma}_1 \right) + b_1 \right\} dt \\ \quad + \left\{ \left[C_1 - D_1 \mathcal{R}_1^{-1} \left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1 \right] \hat{x}_i^* \right. \\ \quad + \left[F_1 - D_1 \mathcal{R}_1^{-1} \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right) \right] \mathbb{E}z - D_1 \mathcal{R}_1^{-1} B_1 \mathbb{E}\varphi \\ \quad \left. - D_1 \mathcal{R}_1^{-1} \left(D_1 P_1 \sigma_1 + \tilde{D}_1 P_1 \tilde{\sigma}_1 \right) + \sigma_1 \right\} dW_i, \\ \hat{x}_i^*(0) = \xi, \end{array} \right. \quad (3.29)$$

and \mathbb{R} -valued function triple $(\mathbb{E}z(\cdot), \mathbb{E}\bar{x}_0(\cdot), \mathbb{E}\varphi)$ satisfies (3.26).

Proof. (3.28) can be obtained from (3.18) since $\hat{\xi}(\cdot) \equiv 0$ in (3.24). (3.29) can be obtained by putting (3.28) into (3.3) and taking the conditional expectation $\mathbb{E}[\cdot | \mathcal{F}_t^{W_i}]$ on both sides of it. The proof is complete. \square

For notational simplicity and noticing (3.25), we represent the state feedback optimal strategies (3.28) of the followers as

$$u_i^* = K_1 \hat{x}_i^* + K_2 \mathbb{E}z + K_3 - \mathcal{R}_1^{-1} B_1 \mathbb{E}\varphi, \quad \mathbb{P}\text{-a.s., a.e.}, \quad (3.30)$$

where

$$\left\{ \begin{array}{l} K_1 := \mathcal{R}_1^{-1} \left(B_1 + D_1 C_1 + \tilde{D}_1 \tilde{C}_1 \right) P_1, \quad K_2 := -\mathcal{R}_1^{-1} \left(B_1 P_2 + D_1 F_1 P_1 + \tilde{D}_1 \tilde{F}_1 P_1 \right), \\ K_3 := -\mathcal{R}_1^{-1} \left(D_1 P_1 \sigma_1 + \tilde{D}_1 P_1 \tilde{\sigma}_1 \right), \end{array} \right.$$

and then

$$\mathbb{E}u_i^* = (K_1 + K_2) \mathbb{E}z + K_3 - \mathcal{R}_1^{-1} B_1 \mathbb{E}\varphi, \quad \text{for } i = 1, \dots, N. \quad (3.31)$$

To conclude this subsection, let's discuss the well-posedness of the CC system (3.14). Similar as Li et al. [23], we essentially employed the Riccati method.

After obtaining the optimal strategies of the followers in their feedback form (3.31), we substitute them into (3.14) to obtain

$$\left\{ \begin{array}{l} d\bar{x}_i^* = [A_1\bar{x}_i^* + B_1(K_1\hat{x}_i^* + K_2\mathbb{E}z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi) + E_1\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + b_1] dt \\ \quad + [C_1\bar{x}_i^* + K_1\hat{x}_i^* + K_2\mathbb{E}z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi + F_1\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \sigma_1] dW_i \\ \quad + [\tilde{C}_1\bar{x}_i^* + K_1\hat{x}_i^* + K_2\mathbb{E}z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi + \tilde{F}_1\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \tilde{\sigma}_1] dW, \\ d\bar{x}_0 = [A_0\bar{x}_0 + B_0u_0 + E_0\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + b_0] dt \\ \quad + [C_0\bar{x}_0 + D_0u_0 + F_0\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \sigma_0] dW_0 \\ \quad + [\tilde{C}_0\bar{x}_0 + \tilde{D}_0u_0 + \tilde{F}_0\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + \tilde{\sigma}_0] dW, \\ dp_i = - [A_1p_i + C_1q_i + \tilde{C}_1\tilde{q}_i - Q_1[\bar{x}_i^* - (\lambda\bar{x}_0 + (1-\lambda)\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W])]] dt \\ \quad + q_i dW_i + \tilde{q}_i dW + q_{i,0} dW_0, \\ \bar{x}_i^*(0) = \xi, \quad \bar{x}_0(0) = \xi_0, \quad p_i(T) = -G_1\bar{x}_i^*(T), \quad \text{for } i = 1, \dots, N. \end{array} \right. \quad (3.32)$$

Since we have already established the solvability of the FBODE (3.26), the first equation of (3.32) is a filtered SDE. Taking $\mathbb{E}[\cdot | \mathcal{F}_t^W]$ on both sides of it, we get

$$\left\{ \begin{array}{l} d\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] = \{(A_1 + E_1)\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + B_1(K_1\mathbb{E}\bar{x}_i^* + K_2\mathbb{E}z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi) + b_1\} dt \\ \quad + \{(\tilde{C}_1 + \tilde{F}_1)\mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W] + K_1\mathbb{E}\bar{x}_i^* + K_2\mathbb{E}z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi + \tilde{\sigma}_1\} dW, \\ \mathbb{E}[\bar{x}_i^* | \mathcal{F}_t^W](0) = \xi, \quad \text{for } i = 1, \dots, N. \end{array} \right. \quad (3.33)$$

This is a linear SDE, we can easily derive its solvability by standard SDE theory. And the solvability of (3.29) of $\hat{x}_i(\cdot)$ can be guaranteed similarly. After these, we find that the first equation of (3.32) is a linear SDE, which is also solvable. And the second equation of (3.32) is a linear SDE, which also admits a unique solution $\bar{x}_0(\cdot)$. Then, the linear BSDE in (3.32) admits a unique solution $(p_i(\cdot), q_i(\cdot), \tilde{q}_i(\cdot), q_{i,0}(\cdot))$. Therefore, the well-posedness of (3.14) is obtained.

3.3 Open loop decentralized strategy of the leader

Noting that the followers take their optimal strategies $u^*(\cdot; u_0) \equiv (u_1^*(\cdot; u_0), \dots, u_N^*(\cdot; u_0))$, the leader \mathcal{A}_0 will face the following “new” centralized state equation

$$\left\{ \begin{array}{l} dx_0 = \left[A_0 x_0 + B_0 u_0 + E_0 x^{*(N)} + b_0 \right] dt + \left[C_0 x_0 + D_0 u_0 + F_0 x^{*(N)} + \sigma_0 \right] dW_0 \\ \quad + \left[\tilde{C}_0 x_0 + \tilde{D}_0 u_0 + \tilde{F}_0 x^{*(N)} + \tilde{\sigma}_0 \right] dW, \\ dx_i^* = \left[A_1 x_i + B_1 (K_1 \hat{x}_i^* + K_2 \mathbb{E} \bar{x}_i^* + K_3 - \mathcal{R}_1^{-1} B_1 \mathbb{E} \varphi) + E_1 x^{*(N)} + b_1 \right] dt \\ \quad + \left[C_1 x_i + D_1 (K_1 \hat{x}_i^* + K_2 \mathbb{E} \bar{x}_i^* + K_3 - \mathcal{R}_1^{-1} B_1 \mathbb{E} \varphi) + F_1 x^{*(N)} + \sigma_1 \right] dW_i \\ \quad + \left[\tilde{C}_1 x_i + \tilde{D}_1 (K_1 \hat{x}_i^* + K_2 \mathbb{E} \bar{x}_i^* + K_3 - \mathcal{R}_1^{-1} B_1 \mathbb{E} \varphi) + \tilde{F}_1 x^{*(N)} + \tilde{\sigma}_1 \right] dW, \\ d\mathbb{E} \varphi = (M_1 \mathbb{E} \varphi + Q_1 \lambda \mathbb{E} \bar{x}_0 + M_2) dt, \\ x_0(0) = \xi_0, \quad x_i^*(0) = \xi, \quad \mathbb{E} \varphi(T) = 0, \quad \text{for } i = 1, \dots, N, \end{array} \right. \quad (3.34)$$

where $x^{*(N)}(\cdot) := \frac{1}{N} \sum_{i=1}^N x_i^*(\cdot)$, whose solution is $(x_0(\cdot), x_1^*(\cdot), \dots, x_N^*(\cdot)) \in L^2_{\mathcal{F}_t}(0, T; \mathbb{R}^{1+N})$, together with $\mathbb{E} \varphi(\cdot) \in \mathbb{R}$.

The centralized cost functional (2.3) of the leader \mathcal{A}_0 now writes

$$\mathcal{J}_0(u_0(\cdot)) = \frac{1}{2} \mathbb{E} \int_0^T \left[R_0 u_0^2 + Q_0 (x_0 - x^{*(N)})^2 \right] dt + G_0 x_0^2(T). \quad (3.35)$$

Then, from (3.1), (3.9), (3.12) and (3.30), the corresponding decentralized state equation of the leader \mathcal{A}_0 is

$$\left\{ \begin{array}{l} d\bar{x}_0 = [A_0 \bar{x}_0 + B_0 u_0 + E_0 z + b_0] dt + [C_0 \bar{x}_0 + D_0 u_0 + F_0 z + \sigma_0] dW_0 \\ \quad + [\tilde{C}_0 \bar{x}_0 + \tilde{D}_0 u_0 + \tilde{F}_0 z + \tilde{\sigma}_0] dW, \\ dz = [(A_1 + E_1) z + B_1 [(K_1 + K_2) \mathbb{E} z + K_3 - \mathcal{R}_1^{-1} B_1 \mathbb{E} \varphi] + b_1] dt \\ \quad + \left[(\tilde{C}_1 + \tilde{F}_1) z + \tilde{D}_1 [(K_1 + K_2) \mathbb{E} z + K_3 - \mathcal{R}_1^{-1} B_1 \mathbb{E} \varphi] + \tilde{\sigma}_1 \right] dW, \\ d\mathbb{E} \varphi = \{M_1 \mathbb{E} \varphi + Q_1 \lambda \mathbb{E} \bar{x}_0 + M_2\} dt, \\ \bar{x}_0(0) = \xi_0, \quad z(0) = \xi, \quad \mathbb{E} \varphi(T) = 0, \end{array} \right. \quad (3.36)$$

and the centralized cost functional is

$$\mathcal{J}_0(u_0(\cdot)) = \frac{1}{2} \mathbb{E} \int_0^T \left[R_0 u_0^2 + Q (\bar{x}_0 - z)^2 \right] dt + G \bar{x}_0^2(T). \quad (3.37)$$

Now, we define the Hamiltonian function $H_0 : [0, T] \times \mathbb{R} \rightarrow \mathbb{R}$

of the leader \mathcal{A}_0 as

$$\begin{aligned}
H_0(\bar{x}_0, z, \mathbb{E}\varphi, y_0, z_0, \tilde{z}_0, g, \tilde{h}, h_0, \eta) &:= y_0 (A_0\bar{x}_0 + B_0u_0 + E_0z + b_0) \\
&+ z_0 (C_0\bar{x}_0 + D_0u_0 + F_0z + \sigma_0) + \tilde{z}_0 \left(\tilde{C}_0\bar{x}_0 + \tilde{D}_0u_0 + \tilde{F}_0z + \tilde{\sigma}_0 \right) \\
&+ g \left[(A_1 + E_1)z + B_1 \left[(K_1 + K_2) \mathbb{E}z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi \right] + b_1 \right] \\
&+ \tilde{h} \left[\left(\tilde{C}_1 + \tilde{F}_1 \right) z + \tilde{D}_1 \left[(K_1 + K_2) \mathbb{E}z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi \right] + \tilde{\sigma}_1 \right] \\
&+ \eta (M_1\mathbb{E}\varphi + Q_1\lambda\mathbb{E}\bar{x}_0 + M_2) - \frac{R_0u_0^2}{2} - \frac{Q_0(\bar{x}_0 - z)^2}{2}.
\end{aligned} \tag{3.38}$$

By applying the stochastic maximum principle with partial information, we can obtain the open-loop decentralized strategies of the leader \mathcal{A}_0 for Problem 3.1 (ii). For simplicity of notation, we let $\tilde{\xi} := \mathbb{E} \left[\xi | \mathcal{F}_t^{W_0} \right]$.

Theorem 3.3. *Let assumption 2.1 and 2.2 hold. Then the open-loop decentralized strategy of the leader \mathcal{A}_0 is given by*

$$u_0^* = R_0^{-1} \left(B_0\check{y}_0 + D_0\check{z}_0 + \tilde{D}_0\check{\check{z}}_0 \right), \quad \mathbb{P}\text{-a.s., a.e.}, \tag{3.39}$$

where $(\bar{x}_0^*(\cdot), z^*(\cdot), \mathbb{E}\varphi^*(\cdot), y_0(\cdot), z_0(\cdot), \tilde{z}_0(\cdot), g(\cdot), \tilde{h}(\cdot), h_0(\cdot), \eta(\cdot))$ satisfies the following stochastic Hamiltonian system

$$\left\{ \begin{aligned}
d\bar{x}_0^* &= \left[A_0\bar{x}_0^* + B_0R_0^{-1} \left(B_0\check{y}_0 + D_0\check{z}_0 + \tilde{D}_0\check{\check{z}}_0 \right) + E_0z^* + b_0 \right] dt \\
&+ \left[C_0\bar{x}_0^* + D_0R_0^{-1} \left(B_0\check{y}_0 + D_0\check{z}_0 + \tilde{D}_0\check{\check{z}}_0 \right) + F_0z^* + \sigma_0 \right] dW_0 \\
&+ \left[\tilde{C}_0\bar{x}_0^* + \tilde{D}_0R_0^{-1} \left(B_0\check{y}_0 + D_0\check{z}_0 + \tilde{D}_0\check{\check{z}}_0 \right) + \tilde{F}_0z^* + \tilde{\sigma}_0 \right] dW, \\
dz^* &= \left[(A_1 + E_1)z^* + B_1 \left[(K_1 + K_2) \mathbb{E}z^* + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi^* \right] + b_1 \right] dt, \\
&+ \left[\left(\tilde{C}_1 + \tilde{F}_1 \right) z^* + \tilde{D}_1 \left[(K_1 + K_2) \mathbb{E}z^* + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}\varphi^* \right] + \tilde{\sigma}_1 \right] dW, \\
d\mathbb{E}\varphi^* &= \{ M_1\mathbb{E}\varphi^* + Q_1\lambda\mathbb{E}\bar{x}_0^* + M_2 \} dt, \\
dy_0 &= - \left(A_0y_0 + C_0z_0 + \tilde{C}_0\tilde{z}_0 - Q_0(\bar{x}_0^* - z^*) + Q_1\lambda\mathbb{E}\eta \right) dt + z_0dW_0 + \tilde{z}_0dW, \\
dg &= - \left(E_0y_0 + F_0z_0 + \tilde{F}_0\tilde{z}_0 + (A_1 + E_1)g + \left(\tilde{C}_1 + \tilde{F}_1 \right) \tilde{h} + Q_0(\bar{x}_0^* - z^*) \right. \\
&\quad \left. + B_1(K_1 + K_2) \mathbb{E}g + \tilde{D}_1(K_1 + K_2) \mathbb{E}h \right) + \tilde{h}dW + h_0dW_0, \\
d\eta &= - \left(-\mathcal{R}_1^{-1}B_1^2\mathbb{E}g - \mathcal{R}_1^{-1}B_1\tilde{D}_1\mathbb{E}\tilde{h} + M_1\mathbb{E}\eta \right) dt, \\
\bar{x}_0^*(0) &= \xi_0, \quad z^*(0) = \xi, \quad \mathbb{E}\varphi^*(T) = 0, \quad y_0(T) = -G_0\bar{x}_0^*(T), \quad g(T) = 0, \quad \eta(0) = 0.
\end{aligned} \right. \tag{3.40}$$

Proof. For small $\varepsilon > 0$, let $u_0^\varepsilon = u_0^* + \varepsilon\delta u_0$, and we denote the solution to the FBSDE (3.40) corresponding with u_0^ε by $(\bar{x}_0^\varepsilon(\cdot), z^\varepsilon(\cdot), \mathbb{E}\varphi^\varepsilon(\cdot))$. Then we have

$$\bar{x}_0^\varepsilon = \bar{x}_0^* + \varepsilon\delta\bar{x}_0, \quad z^\varepsilon = z^* + \varepsilon\delta z, \quad \mathbb{E}\varphi^\varepsilon = \mathbb{E}\varphi^* + \varepsilon\mathbb{E}\delta\varphi,$$

where $(\delta\bar{x}_0(\cdot), \delta z(\cdot), \mathbb{E}[\delta\varphi](\cdot))$ satisfies

$$\left\{ \begin{array}{l} d\delta\bar{x}_0 = [A_0\delta\bar{x}_0 + B_0\delta u_0 + E_0\delta z] dt + [C_0\delta\bar{x}_0 + D_0\delta u_0 + F_0\delta z] dW_0 \\ \quad + [\tilde{C}_0\delta\bar{x}_0 + \tilde{D}_0\delta u_0 + \tilde{F}_0\delta z] dW, \\ d\delta z = \{(A_1 + E_1)\delta z + B_1[(K_1 + K_2)\mathbb{E}\delta z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}[\delta\varphi]]\} dt, \\ \quad + \{(\tilde{C}_1 + \tilde{F}_1)\delta z + \tilde{D}_1[(K_1 + K_2)\mathbb{E}\delta z + K_3 - \mathcal{R}_1^{-1}B_1\mathbb{E}[\delta\varphi]]\} dW, \\ d\mathbb{E}[\delta\varphi] = (M_1\mathbb{E}[\delta\varphi] + Q_1\lambda\mathbb{E}\delta\bar{x}_0 + M_2) dt, \\ \delta\bar{x}_0(0) = 0, \quad \delta z(0) = 0, \quad \mathbb{E}[\delta\varphi](T) = 0. \end{array} \right.$$

Noting (3.37), we have

$$\begin{aligned} & J_0(u_0^*(\cdot) + \varepsilon\delta u_0(\cdot)) - J_0(u_0^*(\cdot)) \\ &= \frac{\varepsilon}{2}\mathbb{E}\left\{\int_0^T \left\{R_0u_0(2u_0^* + \varepsilon\delta u_0) + Q_0(\delta\bar{x}_0 - \delta z)[2(\bar{x}_0^* - z) + \varepsilon(\delta\bar{x}_0 - \delta z)]\right\} dt \right. \\ &\quad \left. + G_0\delta x_0(T)(2\bar{x}_0^*(T) + \varepsilon\delta\bar{x}_0(T))\right\} \\ &= \frac{\varepsilon^2}{2}\mathbb{E}\left\{\int_0^T [R_0\delta u_0^2 + Q_0(\delta\bar{x}_0 - \delta z)^2] dt + G_0\delta\bar{x}_0^2(T)\right\} \\ &\quad + \varepsilon\mathbb{E}\left\{\int_0^T [R_0\delta u_0u_0^* + Q_0(\delta\bar{x}_0 - \delta z)(\bar{x}_0^* - z)] dt + G_0\delta\bar{x}_0(T)\bar{x}_0^*(T)\right\}, \end{aligned}$$

where from (3.40), we get

$$\begin{aligned} & \mathbb{E}[G_0\delta\bar{x}_0(T)\bar{x}_0^*(T)] = \mathbb{E}[-y_0(T)\delta\bar{x}_0(T)] \\ &= -\mathbb{E}[y_0(T)\delta\bar{x}_0(T) - y_0(0)\delta\bar{x}_0(0) + g(T)\delta z(T) - g(0)\delta z(0) + \eta(T)\mathbb{E}[\delta\varphi](T) - \eta(0)\mathbb{E}[\delta\varphi](0)] \\ &= -\mathbb{E}\left\{\int_0^T [B_0y_0\delta u_0 + Q_0\delta x_0(\bar{x}_0^* - z^*) + D_0\delta u_0z_0 + \tilde{D}_0\delta u_0\tilde{z}_0 - Q_0\delta z(x_0^* - z^*)] dt\right\}. \end{aligned}$$

Therefore,

$$\begin{aligned} & J_0(u_0^*(\cdot) + \varepsilon\delta u_0(\cdot)) - J_0(u_0^*(\cdot)) = \frac{\varepsilon^2}{2}\mathbb{E}\left\{\int_0^T [R_0\delta u_0^2 + Q_0(\delta\bar{x}_0 - \delta z)^2] dt + G_0\delta\bar{x}_0^2(T)\right\} \\ &\quad + \varepsilon\mathbb{E}\left\{\int_0^T [\delta u_0(R_0u_0^* - B_0y_0 - D_0z_0 - \tilde{D}_0\tilde{z}_0)] dt\right\}. \end{aligned}$$

Due to the arbitrariness of ε , we finish the proof. \square

Noticing (3.40) is also a CMF-FBSDE, we still discuss its well-posedness in the following subsection.

3.4 Feedback decentralized strategy of the leader

Now, we derive the state feedback of the open loop strategy of the leader \mathcal{A}_0 , by the dimension expansion technique of Yong [40]. Let

$$X := \begin{bmatrix} \bar{x}_0^* \\ z^* \\ \eta \end{bmatrix}, \quad Y := \begin{bmatrix} y_0 \\ g \\ \mathbb{E}\varphi^* \end{bmatrix}, \quad Z_0 := \begin{bmatrix} z_0 \\ h_0 \\ 0 \end{bmatrix}, \quad \tilde{Z} := \begin{bmatrix} \tilde{z}_0 \\ \tilde{h} \\ 0 \end{bmatrix}.$$

Then, the Hamiltonian system (3.40) of the leader \mathcal{A}_0 can be rewritten as

$$\left\{ \begin{array}{l} dX = \left(L_{11}X + L_{12}\mathbb{E}X + L_{13}\mathbb{E}Y + L_{14}\mathbb{E}\tilde{Z} + \mathcal{B}_0u_0^* + f_1 \right) dt \\ \quad + (L_{21}X + \mathcal{D}_0u_0^* + f_2) dW_0 + \left(L_{31}X + L_{32}\mathbb{E}X - L_{14}^\top\mathbb{E}Y + \tilde{\mathcal{D}}_0u_0^* + f_3 \right) dW, \\ dY = \left(N_{11}X + N_{12}\mathbb{E}X - L_{11}^\top Y - L_{12}^\top\mathbb{E}Y - L_{21}^\top Z_0 - L_{31}^\top\tilde{Z} - L_{32}^\top\mathbb{E}\tilde{Z} + f_4 \right) dt \\ \quad + Z_0dW_0 + \tilde{Z}dW, \\ X(0) = \Xi, \quad Y(T) = -\mathcal{G}_0X(T), \end{array} \right. \quad (3.41)$$

where we have denoted

$$\begin{aligned} L_{11} &:= \begin{bmatrix} A_0 & E_0 & 0 \\ 0 & A_1 + E_1 & 0 \\ 0 & 0 & -M_1 \end{bmatrix}, \quad L_{12} := \begin{bmatrix} 0 & 0 & 0 \\ 0 & B_1(K_1 + K_2) & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad \mathcal{B}_0 := \begin{bmatrix} B_0 \\ 0 \\ 0 \end{bmatrix}, \\ L_{13} &:= \begin{bmatrix} 0 & 0 & 0 \\ 0 & 0 & -\mathcal{R}_1^{-1}B_1^2 \\ 0 & \mathcal{R}_1^{-1}B_1^2 & 0 \end{bmatrix}, \quad L_{14} := \begin{bmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & \mathcal{R}_1^{-1}B_1\tilde{D}_1 & 0 \end{bmatrix}, \quad f_1 := \begin{bmatrix} b_0 \\ B_0K_3 + b_1 \\ 0 \end{bmatrix}, \\ L_{21} &:= \begin{bmatrix} C_0 & F_0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad \mathcal{D}_0 := \begin{bmatrix} D_0 \\ 0 \\ 0 \end{bmatrix}, \quad f_2 := \begin{bmatrix} \sigma_0 \\ 0 \\ 0 \end{bmatrix}, \quad L_{31} := \begin{bmatrix} \tilde{C}_0 & \tilde{F}_0 & 0 \\ 0 & \tilde{C}_1 + \tilde{F}_1 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \\ L_{32} &:= \begin{bmatrix} 0 & 0 & 0 \\ 0 & \tilde{D}_1(K_1 + K_2) & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad \tilde{\mathcal{D}}_0 := \begin{bmatrix} \tilde{D}_0 \\ 0 \\ 0 \end{bmatrix}, \quad f_3 := \begin{bmatrix} \tilde{\sigma}_0 \\ \tilde{D}_0K_3 + \tilde{\sigma}_1 \\ 0 \end{bmatrix}, \\ N_{11} &:= \begin{bmatrix} Q_0 & -Q_0 & 0 \\ -Q_0 & Q_0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad N_{12} := \begin{bmatrix} 0 & 0 & -Q_1\lambda \\ 0 & 0 & 0 \\ Q_1\lambda & 0 & 0 \end{bmatrix}, \\ f_4 &:= \begin{bmatrix} 0 \\ 0 \\ M_2 \end{bmatrix}, \quad \Xi := \begin{bmatrix} \xi_0 \\ \xi \\ 0 \end{bmatrix}, \quad \mathcal{G}_0 := \begin{bmatrix} G_0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}. \end{aligned}$$

Noticing the terminal condition of (3.41), we can assume that

$$Y(t) = -\Gamma_1(t)X(t) - \Gamma_2(t)\mathbb{E}X(t) - \Phi(t), \quad t \in [0, T], \quad (3.42)$$

where $\Gamma_1(\cdot)$ and $\Gamma_2(\cdot)$ are deterministic matrix-valued functions satisfying $\Gamma_1(T) = \mathcal{G}_0$ and $\Gamma_2(T) = \mathbf{O}_{3 \times 3}$, and $(\Phi(\cdot), \psi_0(\cdot))$ are an $\mathcal{F}_t^{W_0}$ -adapted process pair of the solution to the following BSDE:

$$\begin{cases} d\Phi = \gamma dt + \psi_0 dW_0, \\ \Phi(T) = \mathbf{O}_{3 \times 3}. \end{cases} \quad (3.43)$$

for some $\mathcal{F}_t^{W_0}$ -adapted process $\gamma(\cdot)$ to be determined later. In addition, from the first equation of (3.41), we have

$$\begin{cases} d\mathbb{E}X = \left[(L_{11} + L_{12}) \mathbb{E}X + L_{13} \mathbb{E}Y + L_{14} \mathbb{E}\tilde{Z} + \mathcal{B}_0 \mathbb{E}u_0^* + f_1 \right] dt, \\ \mathbb{E}X(0) = \Xi. \end{cases} \quad (3.44)$$

Applying Itô's formula, we have

$$\begin{aligned} dY &= -\Gamma_1 dX - \dot{\Gamma}_1 X dt - \dot{\Gamma}_2 \mathbb{E}X dt - \Gamma_2 d\mathbb{E}X - d\Phi \\ &= -\Gamma_1 \left\{ \left(L_{11} X + L_{12} \mathbb{E}X + L_{13} \mathbb{E}Y + L_{14} \mathbb{E}\tilde{Z} + \mathcal{B}_0 u_0^* + f_1 \right) dt \right. \\ &\quad \left. + (L_{21} X + \mathcal{D}_0 u_0^* + f_2) dW_0 + \left(L_{31} X + L_{32} \mathbb{E}X - L_{14}^\top \mathbb{E}Y + \tilde{\mathcal{D}}_0 u_0^* + f_3 \right) dW \right\} \\ &\quad - \dot{\Gamma}_1 X dt - \dot{\Gamma}_2 \mathbb{E}X dt - \Gamma_2 \left[(L_{11} + L_{12}) \mathbb{E}X + L_{13} \mathbb{E}Y + L_{14} \mathbb{E}\tilde{Z} + \mathcal{B}_0 \mathbb{E}u_0^* + f_1 \right] dt \\ &\quad - \gamma dt - \psi_0 dW_0 \\ &= \left(N_{11} X + N_{12} \mathbb{E}X - L_{11}^\top Y - L_{12}^\top \mathbb{E}Y - L_{21}^\top Z_0 - L_{31}^\top \tilde{Z} - L_{32}^\top \mathbb{E}\tilde{Z} + f_4 \right) dt \\ &\quad + Z_0 dW_0 + \tilde{Z} dW. \end{aligned}$$

By comparing the coefficients of the drift terms and the diffusion terms, we obtain

$$\begin{cases} -\gamma = \left(\dot{\Gamma}_1 + \Gamma_1 L_{11} + N_{11} \right) X + \left[\dot{\Gamma}_2 + \Gamma_1 L_{12} + \Gamma_2 (L_{11} + L_{12}) + N_{12} \right] \mathbb{E}X - L_{11}^\top Y \\ \quad + \left[\Gamma_1 L_{13} + \Gamma_2 L_{13} - L_{12}^\top \right] \mathbb{E}Y - L_{21}^\top Z_0 - L_{31}^\top \tilde{Z} + \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \mathbb{E}\tilde{Z} \\ \quad + \Gamma_1 \mathcal{B}_0 u_0^* + \Gamma_2 \mathcal{B}_0 \mathbb{E}u_0^* + \Gamma_1 f_1 + \Gamma_2 f_1 + f_4, \\ Z_0 = -\Gamma_1 L_{21} X - \Gamma_1 \mathcal{D}_0 u_0^* - \Gamma_1 f_2 - \psi_0, \text{ P-a.s.}, \\ \tilde{Z} = -\Gamma_1 L_{31} X - \Gamma_1 L_{32} \mathbb{E}X + \Gamma_1 L_{14}^\top \mathbb{E}Y - \Gamma_1 \tilde{\mathcal{D}}_0 u_0^* - \Gamma_1 f_3, \text{ P-a.s.} \end{cases} \quad (3.45)$$

Taking $\mathbb{E} \left[\cdot | \mathcal{F}_t^{W_0} \right]$ on the both sides of (3.42) and the last two equalities in (3.45), we have

$$\begin{cases} \check{Y} = -\Gamma_1 \check{X} - \Gamma_2 \mathbb{E}X - \check{\Phi}, \\ \check{Z}_0 = -\Gamma_1 L_{21} \check{X} - \Gamma_1 \mathcal{D}_0 u_0^* - \Gamma_1 f_2 - \check{\psi}_0, \text{ P-a.s.}, \\ \check{\check{Z}} = -\Gamma_1 L_{31} \check{X} - \Gamma_1 L_{32} \mathbb{E}X + \Gamma_1 L_{14}^\top \mathbb{E}Y - \Gamma_1 \tilde{\mathcal{D}}_0 u_0^* - \Gamma_1 f_3. \\ = -\Gamma_1 L_{31} \check{X} - \Gamma_1 (L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2) \mathbb{E}X - \Gamma_1 L_{14}^\top \mathbb{E}\Phi - \Gamma_1 \tilde{\mathcal{D}}_0 u_0^* - \Gamma_1 f_3, \text{ P-a.s.} \end{cases} \quad (3.46)$$

Therefore, the open loop decentralized strategy (3.39) of the leader \mathcal{A}_0 can be rewritten as

$$\begin{aligned}
R_0 u_0^* &= \mathcal{B}_0^\top \check{Y} + \mathcal{D}_0^\top \check{Z}_0 + \tilde{\mathcal{D}}_0^\top \check{Z} \\
&= -\mathcal{B}_0^\top (\Gamma_1 \check{X} + \Gamma_2 \mathbb{E}X + \check{\Phi}) - \mathcal{D}_0^\top (\Gamma_1 L_{21} \check{X} + \Gamma_1 \mathcal{D}_0 u_0^* + \Gamma_1 f_2 + \check{\psi}_0) \\
&\quad - \tilde{\mathcal{D}}_0^\top \left[\Gamma_1 L_{31} \check{X} + \Gamma_1 L_{32} \mathbb{E}X - \Gamma_1 L_{14}^\top ((-\Gamma_1 - \Gamma_2) \mathbb{E}X - \mathbb{E}\Phi) \right. \\
&\quad \left. + \Gamma_1 \tilde{\mathcal{D}}_0 u_0^* + \Gamma_1 f_3 \right], \mathbb{P}\text{-a.s., a.e.},
\end{aligned} \tag{3.47}$$

and thus

$$\begin{aligned}
&\left(R_0 + \mathcal{D}_0^\top \Gamma_1 \mathcal{D}_0 + \tilde{\mathcal{D}}_0^\top \Gamma_1 \tilde{\mathcal{D}}_0 \right) u_0^* \\
&= - \left[\left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) \check{X} + \left(\mathcal{B}_0^\top \Gamma_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top (\Gamma_1 + \Gamma_2) \right) \mathbb{E}X \right. \\
&\quad \left. + \mathcal{B}_0^\top \check{\Phi} + \mathcal{D}_0^\top \Gamma_1 f_2 + \mathcal{D}_0^\top \check{\psi}_0 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \mathbb{E}\Phi + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right], \mathbb{P}\text{-a.s., a.e.}
\end{aligned}$$

Assume that

$$\mathbf{Assumption\ 3.2.} \quad \mathcal{R}_0 := R_0 + \mathcal{D}_0^\top \Gamma_1 \mathcal{D}_0 + \tilde{\mathcal{D}}_0^\top \Gamma_1 \tilde{\mathcal{D}}_0 \neq 0,$$

we can get

$$\begin{aligned}
u_0^* &= -\mathcal{R}_0^{-1} \left[\left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) \check{X} \right. \\
&\quad \left. + \left(\mathcal{B}_0^\top \Gamma_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top (\Gamma_1 + \Gamma_2) \right) \mathbb{E}X \right. \\
&\quad \left. + \mathcal{B}_0^\top \check{\Phi} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \mathbb{E}\Phi + \mathcal{D}_0^\top \Gamma_1 f_2 + \mathcal{D}_0^\top \check{\psi}_0 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right], \mathbb{P}\text{-a.s., a.e.},
\end{aligned} \tag{3.48}$$

and

$$\begin{aligned}
\mathbb{E}u_0^* &= -\mathcal{R}_0^{-1} \left[\left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} + \mathcal{B}_0^\top \Gamma_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top (\Gamma_1 + \Gamma_2) \right) \mathbb{E}X \right. \\
&\quad \left. + \left(\mathcal{B}_0^\top + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \right) \mathbb{E}\Phi + \mathcal{D}_0^\top \Gamma_1 f_2 + \mathcal{D}_0^\top \mathbb{E}\psi_0 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right].
\end{aligned} \tag{3.49}$$

Similarly, taking $\mathbb{E} \left[\cdot | \mathcal{F}_t^{W_0} \right]$ on the both sides of the first equality in (3.45), we have

$$\begin{aligned}
-\dot{\gamma} &= \left(\dot{\Gamma}_1 + \Gamma_1 L_{11} + N_{11} \right) \check{X} + \left[\dot{\Gamma}_2 + \Gamma_1 L_{12} + \Gamma_2 (L_{11} + L_{12}) + N_{12} \right] \mathbb{E}X \\
&\quad - L_{11}^\top (-\Gamma_1 \check{X} - \Gamma_2 \mathbb{E}X - \check{\Phi}) + \left(\Gamma_1 L_{13} + \Gamma_2 L_{13} - L_{12}^\top \right) [-(\Gamma_1 + \Gamma_2) \mathbb{E}X - \mathbb{E}\Phi] \\
&\quad - L_{21}^\top (-\Gamma_1 L_{21} \check{X} - \Gamma_1 \mathcal{D}_0 u_0^* - \Gamma_1 f_2 - \check{\psi}_0) - L_{31}^\top \left[-\Gamma_1 L_{31} \check{X} \right. \\
&\quad \left. - \Gamma_1 \left(L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2 \right) \mathbb{E}X - \Gamma_1 L_{14}^\top \mathbb{E}\Phi - \Gamma_1 \tilde{\mathcal{D}}_0^* u_0^* - \Gamma_1 f_3 \right] \\
&\quad + \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \left[-\Gamma_1 \left(L_{31} + L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2 \right) \mathbb{E}X \right. \\
&\quad \left. - \Gamma_1 L_{14}^\top \mathbb{E}\Phi - \Gamma_1 \tilde{\mathcal{D}}_0 \mathbb{E}u_0^* - \Gamma_1 f_3 \right] + \Gamma_1 \mathcal{B}_0 u_0^* + \Gamma_2 \mathcal{B}_0 \mathbb{E}u_0^* + \Gamma_1 f_1 + \Gamma_2 f_1 + f_4
\end{aligned}$$

$$\begin{aligned}
&= \left(\dot{\Gamma}_1 + \Gamma_1 L_{11} + N_{11} + L_{11}^\top \Gamma_1 + L_{21}^\top \Gamma_1 L_{21} + L_{31}^\top \Gamma_1 L_{31} \right) \check{X} \\
&\quad + \left[\dot{\Gamma}_2 + \Gamma_1 L_{12} + \Gamma_2 L_{11} + \Gamma_2 L_{12} + N_{12} + L_{11}^\top \Gamma_2 - \Gamma_1 L_{13} (\Gamma_1 + \Gamma_2) \right. \\
&\quad - \Gamma_2 L_{13} (\Gamma_1 + \Gamma_2) + L_{12}^\top (\Gamma_1 + \Gamma_2) + L_{31}^\top \Gamma_1 L_{32} + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_1 + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_2 \\
&\quad \left. - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \left(L_{31} + L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2 \right) \right] \mathbb{E}X \\
&\quad + \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) u_0^* + \left[\Gamma_2 \mathcal{B}_0 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \tilde{\mathcal{D}}_0 \right] \mathbb{E}u_0^* \\
&\quad + L_{11}^\top \check{\Phi} + \left[-\Gamma_1 L_{13} - \Gamma_2 L_{13} + L_{12}^\top + L_{31}^\top \Gamma_1 L_{14}^\top - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 L_{14}^\top \right] \mathbb{E}\Phi \\
&\quad + L_{21}^\top \check{\psi}_0 + L_{21}^\top \Gamma_1 f_2 + L_{31}^\top \Gamma_1 f_3 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 f_3 + \Gamma_1 f_1 + \Gamma_2 f_1 + f_4.
\end{aligned}$$

Substituting (3.48) and (3.49) into the above equation, we get

$$\begin{aligned}
-\tilde{\gamma} &= \left(\dot{\Gamma}_1 + \Gamma_1 L_{11} + N_{11} + L_{11}^\top \Gamma_1 + L_{21}^\top \Gamma_1 L_{21} + L_{31}^\top \Gamma_1 L_{31} \right) \check{X} \\
&\quad + \left[\dot{\Gamma}_2 + \Gamma_1 L_{12} + \Gamma_2 L_{11} + \Gamma_2 L_{12} + N_{12} + L_{11}^\top \Gamma_2 - \Gamma_1 L_{13} (\Gamma_1 + \Gamma_2) \right. \\
&\quad - \Gamma_2 L_{13} (\Gamma_1 + \Gamma_2) + L_{12}^\top (\Gamma_1 + \Gamma_2) + L_{31}^\top \Gamma_1 L_{32} + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_1 + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_2 \\
&\quad \left. - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \left(L_{31} + L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2 \right) \right] \mathbb{E}X \\
&\quad + \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) \mathcal{R}_0^{-1} \left[\left(-\mathcal{B}_0^\top \Gamma_1 - \mathcal{D}_0^\top \Gamma_1 L_{21} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) \check{X} \right. \\
&\quad + \left(-\mathcal{B}_0^\top \Gamma_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) \mathbb{E}X - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \mathbb{E}\Phi - \mathcal{B}_0^\top \check{\Phi} \\
&\quad \left. - \mathcal{D}_0^\top \Gamma_1 f_2 - \mathcal{D}_0^\top \check{\psi}_0 - \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right] + \left[\Gamma_2 \mathcal{B}_0 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \tilde{\mathcal{D}}_0 \right] \mathcal{R}_0^{-1} \\
&\quad \left[\left(-\mathcal{B}_0^\top \Gamma_1 - \mathcal{D}_0^\top \Gamma_1 L_{21} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} - \mathcal{B}_0^\top \Gamma_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) \mathbb{E}X \right. \\
&\quad \left. + \left(-\tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top - \mathcal{B}_0^\top \right) \mathbb{E}\Phi - \mathcal{D}_0^\top \Gamma_1 f_2 - \mathcal{D}_0^\top \mathbb{E}\psi_0 - \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right] + L_{11}^\top \check{\Phi} \\
&\quad + \left[-\Gamma_1 L_{13} - \Gamma_2 L_{13} + L_{12}^\top + L_{31}^\top \Gamma_1 L_{14}^\top - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 L_{14}^\top \right] \mathbb{E}\Phi \\
&\quad + L_{21}^\top \check{\psi}_0 + L_{21}^\top \Gamma_1 f_2 + L_{31}^\top \Gamma_1 f_3 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 f_3 + \Gamma_1 f_1 + \Gamma_2 f_1 + f_4 \\
&= \left\{ \left[\dot{\Gamma}_1 + \Gamma_1 L_{11} + N_{11} + L_{11}^\top \Gamma_1 + L_{21}^\top \Gamma_1 L_{21} + L_{31}^\top \Gamma_1 L_{31} \right. \right. \\
&\quad \left. + \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) \mathcal{R}_0^{-1} \left(-\mathcal{B}_0^\top \Gamma_1 - \mathcal{D}_0^\top \Gamma_1 L_{21} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) \right] \check{X} \\
&\quad + \left\{ \dot{\Gamma}_2 + \Gamma_1 L_{12} + \Gamma_2 L_{11} + \Gamma_2 L_{12} + N_{12} + L_{11}^\top \Gamma_2 - \Gamma_1 L_{13} (\Gamma_1 + \Gamma_2) \right. \\
&\quad - \Gamma_2 L_{13} (\Gamma_1 + \Gamma_2) + L_{12}^\top (\Gamma_1 + \Gamma_2) + L_{31}^\top \Gamma_1 L_{32} + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_1 + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_2 \\
&\quad - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \left(L_{31} + L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2 \right) \\
&\quad \left. + \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) \mathcal{R}_0^{-1} \left(-\mathcal{B}_0^\top \Gamma_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) \right. \\
&\quad \left. + \left[\Gamma_2 \mathcal{B}_0 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \tilde{\mathcal{D}}_0 \right] \mathcal{R}_0^{-1} \left(-\mathcal{B}_0^\top \Gamma_1 - \mathcal{D}_0^\top \Gamma_1 L_{21} \right. \right. \\
&\quad \left. \left. - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} - \mathcal{B}_0^\top \Gamma_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) \right\} \mathbb{E}X
\end{aligned}$$

$$\begin{aligned}
& + \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) \mathcal{R}_0^{-1} \left(-\mathcal{B}_0^\top \check{\Phi} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \mathbb{E}\Phi - \mathcal{D}_0^\top \check{\psi}_0 - \mathcal{D}_0^\top \Gamma_1 f_2 \right. \\
& \left. - \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right) + \left[\Gamma_2 \mathcal{B}_0 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \tilde{\mathcal{D}}_0 \right] \mathcal{R}_0^{-1} \\
& \times \left[\left(-\tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top - \mathcal{B}_0^\top \right) \mathbb{E}\Phi - \mathcal{D}_0^\top \mathbb{E}\psi_0 - \mathcal{D}_0^\top \Gamma_1 f_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right] + L_{11}^\top \check{\Phi} \\
& + \left[-\Gamma_1 L_{13} - \Gamma_2 L_{13} + L_{12}^\top + L_{31}^\top \Gamma_1 L_{14}^\top - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 L_{14}^\top \right] \mathbb{E}\Phi \\
& + L_{21}^\top \check{\psi}_0 + L_{21}^\top \Gamma_1 f_2 + L_{31}^\top \Gamma_1 f_3 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 f_3 + \Gamma_1 f_1 + \Gamma_2 f_1 + f_4.
\end{aligned}$$

Then, we can get the equation of $\Gamma_1(\cdot)$:

$$\begin{cases} \dot{\Gamma}_1 + \Gamma_1 L_{11} + N_{11} + L_{11}^\top \Gamma_1 + L_{21}^\top \Gamma_1 L_{21} + L_{31}^\top \Gamma_1 L_{31} \\ + \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) \mathcal{R}_0^{-1} \left(-\mathcal{B}_0^\top \Gamma_1 - \mathcal{D}_0^\top \Gamma_1 L_{21} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) = 0, \\ \Gamma_1(T) = \mathcal{G}_0, \end{cases} \quad (3.50)$$

the equation of $\Gamma_2(\cdot)$:

$$\begin{cases} \dot{\Gamma}_2 + \Gamma_1 L_{12} + \Gamma_2 L_{11} + \Gamma_2 L_{12} + N_{12} + L_{11}^\top \Gamma_2 - \Gamma_1 L_{13} (\Gamma_1 + \Gamma_2) \\ - \Gamma_2 L_{13} (\Gamma_1 + \Gamma_2) + L_{12}^\top (\Gamma_1 + \Gamma_2) + L_{31}^\top \Gamma_1 L_{32} + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_1 + L_{31}^\top \Gamma_1 L_{14}^\top \Gamma_2 \\ - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \left(L_{31} + L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2 \right) \\ + \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) \mathcal{R}_0^{-1} \left(-\mathcal{B}_0^\top \Gamma_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 \right. \\ \left. - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) + \left[\Gamma_2 \mathcal{B}_0 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \tilde{\mathcal{D}}_0 \right] \mathcal{R}_0^{-1} \left(-\mathcal{B}_0^\top \Gamma_1 \right. \\ \left. - \mathcal{D}_0^\top \Gamma_1 L_{21} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} - \mathcal{B}_0^\top \Gamma_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) = 0, \\ \Gamma_2(T) = \mathcal{O}_{3 \times 3}, \end{cases} \quad (3.51)$$

and the BSDE of $(\check{\Phi}(\cdot), \check{\psi}_0(\cdot))$:

$$\begin{cases} -d\check{\Phi} = \left\{ \left(L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 \right) \mathcal{R}_0^{-1} \left[-\mathcal{B}_0^\top \check{\Phi} - \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \mathbb{E}\Phi - \mathcal{D}_0^\top \check{\psi}_0 \right. \right. \\ \left. \left. - \mathcal{D}_0^\top \Gamma_1 f_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right] + \left[\Gamma_2 \mathcal{B}_0 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 \tilde{\mathcal{D}}_0 \right] \mathcal{R}_0^{-1} \right. \\ \left. \times \left[\left(-\tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top - \mathcal{B}_0^\top \right) \mathbb{E}\Phi - \mathcal{D}_0^\top \mathbb{E}\psi_0 - \mathcal{D}_0^\top \Gamma_1 f_2 - \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right] + L_{11}^\top \check{\Phi} \right. \\ \left. + \left[-\Gamma_1 L_{13} - \Gamma_2 L_{13} + L_{12}^\top + L_{31}^\top \Gamma_1 L_{14}^\top - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 L_{14}^\top \right] \mathbb{E}\Phi \right. \\ \left. + L_{21}^\top \check{\psi}_0 + L_{21}^\top \Gamma_1 f_2 + L_{31}^\top \Gamma_1 f_3 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 f_3 \right. \\ \left. + \Gamma_1 f_1 + \Gamma_2 f_1 + f_4 \right\} dt - \check{\psi}_0 dW_0, \\ \check{\Phi}(T) = \mathcal{O}_{3 \times 3}. \end{cases} \quad (3.52)$$

respectively. By the existence and uniqueness of the solution to the mean-field type BSDE [24]

again, (3.52) degenerates to

$$\left\{ \begin{array}{l} -d\mathbb{E}\Phi = \left\{ \left[L_{11}^\top + L_{21}^\top + (L_{31} + L_{32})^\top \Gamma_1 L_{14}^\top - (\Gamma_1 + \Gamma_2) \left(L_{13} + L_{14} \Gamma_1 L_{14}^\top \right) \right. \right. \\ \quad \left. \left. - \left[L_{21}^\top \Gamma_1 \mathcal{D}_0 + L_{31}^\top \Gamma_1 \tilde{\mathcal{D}}_0 + \Gamma_1 \mathcal{B}_0 + \Gamma_2 \mathcal{B}_0 + \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} + L_{32}^\top \right) \Gamma_1 \tilde{\mathcal{D}}_0 \right] \right. \right. \\ \quad \left. \left. \times \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \right) \right\} \mathbb{E}\Phi + \left[(\Gamma_1 + \Gamma_2) \left(L_{14} \Gamma_2 \tilde{\mathcal{D}}_0 - \mathcal{B}_0 \right) \right. \\ \quad \left. - (L_{21} + L_{31} + L_{32})^\top \Gamma_1 \tilde{\mathcal{D}}_0 \right] \mathcal{R}_0^{-1} \left(\mathcal{D}_0^\top \Gamma_1 f_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right) + L_{21}^\top \Gamma_1 f_2 \\ \quad \left. + L_{31}^\top \Gamma_1 f_3 - \left(\Gamma_1 L_{14} + \Gamma_2 L_{14} - L_{32}^\top \right) \Gamma_1 f_3 + \Gamma_1 f_1 + \Gamma_2 f_1 + f_4 \right\} dt, \end{array} \right. \quad (3.53)$$

$$\mathbb{E}\Phi(T) = \mathbf{O}_{3 \times 3}.$$

Remark 3.2. We note that (3.50) is symmetric Riccati equation, which admits unique solution by applying the Theorem 3.7 of [23]. But (3.51) is an asymmetric one, which is hard to solve in general. In this paper, we need to assume the solvability of (3.51). Then noticing the equation (3.53) is linear BODE, which obviously admits a unique solution.

Therefore, the feedback decentralized strategy of the leader \mathcal{A}_0 can be given in the following.

Theorem 3.4. Let assumptions 2.1, 2.2, 3.1 and 3.2 hold. Let $\Gamma_1(\cdot)$ be the solution to (3.50), and suppose that (3.51) admits a unique solution $\Gamma_2(\cdot)$, then the feedback decentralized strategy of the leader \mathcal{A}_0 can be represented as

$$u_0^* = -\mathcal{R}_0^{-1} \left[\left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) \check{X} + \left(\mathcal{B}_0^\top \Gamma_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 \right. \right. \\ \left. \left. + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) \mathbb{E}X + \left(\mathcal{B}_0^\top + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \right) \mathbb{E}\Phi + \mathcal{D}_0^\top \Gamma_1 f_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right], \quad \mathbb{P}\text{-a.s., a.e.}, \quad (3.54)$$

where $\check{X}(\cdot) \in L^2_{\mathcal{F}_t} (0, T; \mathbb{R}^3)$ satisfied the following SDE:

$$\left\{ \begin{array}{l} d\check{X} = \left\{ \left[L_{11} - \left(\mathcal{B}_0 - L_{14} \Gamma_1 \tilde{\mathcal{D}}_0 \right) \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) \right] \check{X} \right. \\ \quad \left. + \left[L_{12} - \left(L_{13} + L_{14} \Gamma_1 L_{14}^\top \right) (\Gamma_1 + \Gamma_2) - L_{14} \Gamma_1 (L_{31} + L_{32}) \right. \right. \\ \quad \left. \left. - \left(\mathcal{B}_0 - L_{14} \Gamma_1 \tilde{\mathcal{D}}_0 \right) \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top \Gamma_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) \right] \mathbb{E}X \right. \\ \quad \left. - \left[L_{13} + L_{14} \Gamma_1 L_{14}^\top + \left(\mathcal{B}_0 - L_{14} \Gamma_1 \tilde{\mathcal{D}}_0 \right) \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \right) \right] \mathbb{E}\Phi \right. \\ \quad \left. + f_1 - L_{14} \Gamma_1 f_3 - \left(\mathcal{B}_0 - L_{14} \Gamma_1 \tilde{\mathcal{D}}_0 \right) \mathcal{R}_0^{-1} \left(\mathcal{D}_0^\top \Gamma_1 f_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right) \right\} dt \\ \quad + \left\{ \left[L_{21} - \mathcal{D}_0 \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right) \right] \check{X} \right. \\ \quad \left. - \mathcal{D}_0 \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top \Gamma_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right) \mathbb{E}X \right. \\ \quad \left. - \mathcal{D}_0 \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \right) \mathbb{E}\Phi - \mathcal{D}_0 \mathcal{R}_0^{-1} \left(\mathcal{D}_0^\top \Gamma_1 f_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right) \right\} dW_0, \\ \check{X}(0) = \Xi, \end{array} \right. \quad (3.55)$$

$\mathbb{E}X(\cdot) \in \mathbb{R}^3$ satisfies the following ODE:

$$\left\{ \begin{array}{l} d\mathbb{E}X = \left\{ \left[L_{11} + L_{12} - \left(L_{13} + L_{14}\Gamma_1 L_{14}^\top \right) (\Gamma_1 + \Gamma_2) - L_{14}\Gamma_1 (L_{31} + L_{32}) \right. \right. \\ \quad - \left(\mathcal{B}_0 - L_{14}\Gamma_1 \tilde{\mathcal{D}}_0 \right) \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{B}_0^\top \Gamma_2 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right. \\ \quad \left. \left. + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right] \mathbb{E}X \right. \\ \quad \left. - \left[L_{13} + L_{14}\Gamma_1 L_{14}^\top + \left(\mathcal{B}_0 - L_{14}\Gamma_1 \tilde{\mathcal{D}}_0 \right) \mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \right) \right] \mathbb{E}\Phi \right. \\ \quad \left. + f_1 - L_{14}\Gamma_1 f_3 - \left(\mathcal{B}_0 - L_{14}\Gamma_1 \tilde{\mathcal{D}}_0 \right) \mathcal{R}_0^{-1} \left(\mathcal{D}_0^\top \Gamma_1 f_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right) \right\} dt, \\ \mathbb{E}X(0) = \Xi, \end{array} \right. \quad (3.56)$$

and $\mathbb{E}\Phi(\cdot) \in \mathbb{R}^3$ satisfies the BODE (3.53), respectively.

Proof. (3.54) can be obtained by (3.48) with $\check{\Phi}(t) \equiv \mathbb{E}\Phi(t), t \in [0, T]$. (3.55) can be achieved from the first equation of X in (3.41), noting (3.43), the third equality in (3.46) and (3.54). And (3.56) can be got by (3.55) directly. The proof is complete. \square

Similar to the subsection 3.2, in brief, we discuss the well-posedness of (3.41), which is equivalent to (3.40). For simplicity of notation, by (3.54) we denote

$$u_0^* = \theta_1 \check{X} + \theta_2 \mathbb{E}X + \theta_3 \mathbb{E}\Phi + \theta_4, \quad \mathbb{P}\text{-a.s., a.e.}, \quad (3.57)$$

where

$$\left\{ \begin{array}{l} \theta_1 := -\mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top \Gamma_1 + \mathcal{D}_0^\top \Gamma_1 L_{21} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{31} \right), \\ \theta_2 := -\mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top \Gamma_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{32} + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_1 + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \Gamma_2 \right), \\ \theta_3 := -\mathcal{R}_0^{-1} \left(\mathcal{B}_0^\top + \tilde{\mathcal{D}}_0^\top \Gamma_1 L_{14}^\top \right), \\ \theta_4 := -\mathcal{R}_0^{-1} \left(\mathcal{D}_0^\top \Gamma_1 f_2 + \tilde{\mathcal{D}}_0^\top \Gamma_1 f_3 \right). \end{array} \right.$$

Noticing (3.46) and (3.54), the first equation of (3.41) becomes

$$\left\{ \begin{array}{l} dX = \left\{ L_{11}X + \left[L_{12} - L_{13} \left(\Gamma_1 + \Gamma_2 \right) - L_{14} \left(\Gamma_1 L_{31} + \Gamma_1 L_{32} + \Gamma_1 L_{14}^\top \Gamma_1 + \Gamma_1 L_{14}^\top \Gamma_2 \right) \right] \mathbb{E}X \right. \\ \quad - \left(L_{13} + L_{14}\Gamma_1 L_{14}^\top \right) \mathbb{E}\Phi + L_{14}\Gamma_1 \tilde{\mathcal{D}}_0 \left[\left(\theta_1 + \theta_2 \right) \mathbb{E}X + \theta_3 \mathbb{E}\Phi + \theta_4 \right] \\ \quad \left. + \mathcal{B}_0 \left(\theta_1 \check{X} + \theta_2 \mathbb{E}X + \theta_3 \mathbb{E}\Phi + \theta_4 \right) + f_1 \right\} dt \\ \quad + \left[L_{21}X + \mathcal{D}_0 \left(\theta_1 \check{X} + \theta_2 \mathbb{E}X + \theta_3 \mathbb{E}\Phi + \theta_4 \right) + f_2 \right] dW_0 \\ \quad + \left[L_{31}X + \left(L_{32} + L_{14}^\top \Gamma_1 + L_{14}^\top \Gamma_2 \right) \mathbb{E}X + \tilde{\mathcal{D}}_0 \left(\theta_1 \check{X} + \theta_2 \mathbb{E}X + \theta_3 \mathbb{E}\Phi + \theta_4 \right) + f_3 \right] dW, \\ X(0) = \Xi. \end{array} \right. \quad (3.58)$$

Similar as subsection 3.2, we can obtain the solvability of (3.58). And then, we can obtain the solvability of the second equation of (3.41). The details of the proof are left to the interested readers.

4 ε -Stackelberg-Nash equilibria analysis

In Section 3, we derived the decentralized Stackelberg-Nash equilibrium, denoted as $(u_0^*(\cdot), u^*(\cdot) \equiv (u_1^*(\cdot), u_2^*(\cdot), \dots, u_N^*(\cdot)))$, for the limiting Problem 3.1. In this section, we will prove that the decentralized strategies $(u_0^*(\cdot), u^*(\cdot))$ satisfy the ε -Stackelberg-Nash equilibrium property, for Problem 2.1. To begin with, let's define what an ε -Stackelberg-Nash equilibrium entails.

Definition 4.1. *A strategy $(u_0^*(\cdot), u_1^*(\cdot), \dots, u_N^*(\cdot))$ is said to be an ε -Stackelberg-Nash equilibrium for Problem 2.1, if there exists a non-negative value $\varepsilon = \varepsilon(N)$ such that $\lim_{N \rightarrow \infty} \varepsilon(N) = 0$, which satisfies:*

(i) *Given $u_0 \in \mathcal{U}_0^{l,d}$, for $i = 1, \dots, N$, finding the control strategy $u^*(\cdot; u_0) \equiv (u_1^*(\cdot; u_0), \dots, u_N^*(\cdot; u_0))$ such that for any $u_i(\cdot) \in \mathcal{U}_i^{f,d}$,*

$$\mathcal{J}_i(u_i^*(\cdot; u_0); u_{-i}^*(\cdot; u_0)) \leq \mathcal{J}_i(u_i(\cdot); u_{-i}^*(\cdot; u_0)) + \varepsilon;$$

(ii) *finding the control strategy $u_0^*(\cdot; u^*(\cdot))$ such that for any $u_0(\cdot) \in \mathcal{U}_0^{l,d}$,*

$$\mathcal{J}_0(u_0^*(\cdot; u^*(\cdot))) \leq \mathcal{J}_0(u_0(\cdot; u^*(\cdot))) + \varepsilon.$$

The main result of this section is the following theorem.

Theorem 4.1. *Let assumptions 2.1, 2.2 and 3.1 hold, then the set of strategies $(u_0^*(\cdot), u_1^*(\cdot), u_2^*(\cdot), \dots, u_N^*(\cdot))$ constitutes an ε -Stackelberg-Nash equilibrium for Problem 2.1, where*

$$\begin{cases} u_i^* = R_1^{-1} \left(B_1 \hat{p}_i + D_1 \hat{q}_i + \tilde{D}_1 \tilde{\hat{q}}_i \right), & i = 1, 2, \dots, N, \\ u_0^* = R_0^{-1} \left(B_0 \check{y}_0 + D_0 \check{z}_0 + \tilde{D}_0 \tilde{\check{z}}_0 \right), \end{cases} \quad (4.1)$$

with $(p_i(\cdot), q_i(\cdot), \tilde{q}_i(\cdot))$, $(y_0(\cdot), z_0(\cdot), \tilde{z}_0(\cdot))$ satisfying (3.6), (3.40), respectively.

To establish this theorem, we shall present several lemmas.

Lemma 4.1.

$$\mathbb{E} \left[\sup_{0 \leq t \leq T} |x^{*(N)}(t) - z(t)|^2 \right] = O \left(\frac{1}{N} \right), \quad (4.2)$$

$$\sup_{1 \leq i \leq N} \mathbb{E} \left[\sup_{0 \leq t \leq T} |x_i^*(t) - \bar{x}_i^*(t)|^2 \right] = O \left(\frac{1}{N} \right), \quad (4.3)$$

$$\mathbb{E} \left[\sup_{0 \leq t \leq T} |x_0(t) - \bar{x}_0(t)|^2 \right] = O \left(\frac{1}{N} \right). \quad (4.4)$$

Proof. From (2.2), we get

$$\left\{ \begin{aligned} dx^{*(N)}(t) &= \left[(A_1 + E_1)x^{*(N)} + B_1 \frac{1}{N} \sum_{i=1}^N u_i^* + b_1 \right] dt \\ &+ \frac{1}{N} \sum_{i=1}^N \left[C_1 x_i^* + D_1 u_i^* + F_1 x^{*(N)} + \sigma_1 \right] dW_i \\ &+ \left[(\tilde{C}_1 + \tilde{F}_1)x^{*(N)} + \tilde{D}_1 \frac{1}{N} \sum_{i=1}^N u_i^* + \tilde{\sigma}_1 \right] dW, \\ x^{*(N)}(0) &= \xi. \end{aligned} \right. \quad (4.5)$$

Then, by (3.12) we obtain

$$\left\{ \begin{aligned} d(x^{*(N)} - z) &= \left[(A_1 + E_1)(x^{*(N)} - z) + B_1 \left(\frac{1}{N} \sum_{i=1}^N u_i^* - \mathbb{E}u_i^* \right) \right] dt \\ &+ \frac{1}{N} \sum_{i=1}^N \left[C_1 x_i^* + D_1 u_i^* + F_1 x^{*(N)} + \sigma_1 \right] dW_i \\ &+ \left[(\tilde{C}_1 + \tilde{F}_1)(x^{*(N)} - z) + \tilde{D}_1 \left(\frac{1}{N} \sum_{i=1}^N u_i^* - \mathbb{E}u_i^* \right) \right] dW, \\ (x^{*(N)} - z)(0) &= 0. \end{aligned} \right.$$

By using BDG's inequality and standard estimates of SDEs, we have for some positive constant K (may be different line by line),

$$\begin{aligned} &\mathbb{E} \left[\sup_{0 \leq s \leq t} |x^{*(N)}(s) - z(s)|^2 \right] \\ &\leq K \mathbb{E} \int_0^t \left(\sup_{0 \leq r \leq s} |x^{*(N)}(r) - z(r)|^2 + \left| \frac{1}{N} \sum_{i=1}^N u_i^*(r) - \mathbb{E}u_i^*(r) \right|^2 \right) ds \\ &+ \frac{K}{N^2} \mathbb{E} \left[\sum_{i=1}^N \int_0^t (C_1 x_i^* + D_1 u_i^* + F_1 x^{*(N)} + \sigma_1) dW_i \right]^2, \end{aligned}$$

where

$$\begin{aligned} &\frac{1}{N^2} \mathbb{E} \left[\sum_{i=1}^N \int_0^t (C_1 x_i^* + D_1 u_i^* + F_1 x^{*(N)} + \sigma_1) dW_i \right]^2 \\ &= \frac{1}{N^2} \mathbb{E} \left[\sum_{i=1}^N \int_0^t (C_1 x_i^* + D_1 u_i^* + F_1 x^{*(N)} + \sigma_1)^2 dW_i \right. \\ &\quad + 2 \sum_{i < j} \int_0^t (C_1 x_i^* + D_1 u_i^* + F_1 x^{*(N)} + \sigma_1) dW_i \\ &\quad \left. \times \int_0^t (C_1 x_j^* + D_1 u_j^* + F_1 x^{*(N)} + \sigma_1) dW_j \right] \leq \frac{K}{N}. \end{aligned}$$

Therefore,

$$\begin{aligned} & \mathbb{E} \left[\sup_{0 \leq s \leq t} \left| x^{*(N)}(s) - z(s) \right|^2 \right] \\ & \leq K \mathbb{E} \left(\int_0^t \sup_{0 \leq r \leq s} \left| x^{*(N)}(r) - z(r) \right|^2 + \left| \frac{1}{N} \sum_{i=1}^N u_i^*(r) - \mathbb{E} u_i^*(r) \right|^2 \right) ds + O \left(\frac{1}{N} \right). \end{aligned} \quad (4.6)$$

Moreover, noticing that u_i^* and u_j^* are i.i.d., we get

$$\mathbb{E} \int_0^t \left| \frac{1}{N} \sum_{i=1}^N u_i^*(r) - \mathbb{E} u_i^*(r) \right|^2 ds = \frac{1}{N^2} \sum_{i=1}^N \mathbb{E} \int_0^t |u_i^*(r) - \mathbb{E} u_i^*(r)|^2 ds \leq \frac{K}{N} = O \left(\frac{1}{N} \right).$$

From (4.6), by applying Gronwall's inequality, (4.2) holds. Then, by (4.2) and standard estimates of SDEs, (4.3) and (4.4) hold. The proof is complete. \square

Lemma 4.2.

$$|\mathcal{J}_i(u_i^*(\cdot), u_{-i}^*(\cdot)) - J_i(u_i^*(\cdot))| = O \left(\frac{1}{\sqrt{N}} \right), \quad (4.7)$$

$$|\mathcal{J}_0(u_0^*(\cdot)) - J_0(u_0^*(\cdot))| = O \left(\frac{1}{\sqrt{N}} \right). \quad (4.8)$$

Proof. From (2.4) and (3.4), we get

$$\begin{aligned} & |\mathcal{J}_i(u_i^*(\cdot), u_{-i}^*(\cdot)) - J_i(u_i^*(\cdot))| \\ & = \frac{1}{2} \mathbb{E} \left\{ \int_0^T \left\{ Q_1 \left[x_i^* - (\lambda x_0 + (1-\lambda)x^{*(N)}) \right]^2 - Q_1 \left[\bar{x}_i^* - (\lambda \bar{x}_0 + (1-\lambda)z) \right]^2 \right\} dt \right. \\ & \quad \left. + G_1 \left[x_i^{*2}(T) - \bar{x}_i^{*2}(T) \right] \right\}. \end{aligned}$$

Noting Lemma 4.1, we can obtain

$$\begin{aligned} & \frac{1}{2} \mathbb{E} \int_0^T \left\{ Q_1 \left[x_i^* - (\lambda x_0 + (1-\lambda)x^{*(N)}) \right]^2 - Q_1 \left[\bar{x}_i^* - (\lambda \bar{x}_0 + (1-\lambda)z) \right]^2 \right\} dt \\ & = \frac{1}{2} \mathbb{E} \int_0^T \left\{ Q_1 \left[x_i^* - \bar{x}_i^* - \lambda(x_0 - \bar{x}_0) - (1-\lambda)(x^{*(N)} - z) \right]^2 \right. \\ & \quad \left. + 2 \left[\bar{x}_i^* - (\lambda \bar{x}_0 + (1-\lambda)z) \right] \left[x_i^* - \bar{x}_i^* - \lambda(x_0 - \bar{x}_0) - (1-\lambda)(x^{*(N)} - z) \right] \right\} dt \\ & \leq \frac{1}{2} \mathbb{E} \int_0^T \left\{ K \left(|x_i^* - \bar{x}_i^*|^2 + |x_0 - \bar{x}_0|^2 + |x^{*(N)} - z|^2 \right) + \left(\int_0^T \left[\bar{x}_i^* - (\lambda \bar{x}_0 + (1-\lambda)z) \right]^2 dt \right)^{\frac{1}{2}} \right. \\ & \quad \left. \times \left(\int_0^T \left[x_i^* - \bar{x}_i^* - \lambda(x_0 - \bar{x}_0) - (1-\lambda)(x^{*(N)} - z) \right]^2 dt \right)^{\frac{1}{2}} \right\} dt \end{aligned}$$

$$\begin{aligned}
&\leq K\mathbb{E} \int_0^T \left(|x_i^* - \bar{x}_i^*|^2 + |x_0 - \bar{x}_0|^2 + |x^{*(N)} - z|^2 \right) dt \\
&\quad + K\mathbb{E} \left[\int_0^T |x_i^* - \bar{x}_i^*|^2 dt \right]^{\frac{1}{2}} + K\mathbb{E} \left[\int_0^T |x_0^* - \bar{x}_0^*|^2 dt \right]^{\frac{1}{2}} + K\mathbb{E} \left[\int_0^T |x^{*(N)} - z|^2 dt \right]^{\frac{1}{2}} \\
&= O\left(\frac{1}{\sqrt{N}}\right).
\end{aligned}$$

Similarly, the order of the terminal term is also $O\left(\frac{1}{\sqrt{N}}\right)$. Therefore, (4.7) is proved. And then,

$$\begin{aligned}
&|\mathcal{J}_0(u_0^*(\cdot)) - J_0(u_0^*(\cdot))| \\
&= \frac{1}{2}\mathbb{E} \left\{ \int_0^T \left[Q_0(x_0^* - x^{*(N)})^2 - Q_0(\bar{x}_0^* - z)^2 \right] dt + G_1[x_0^{*2}(T) - \bar{x}_0^{*2}(T)] \right\}.
\end{aligned}$$

Using similar method, we can prove (4.8). The proof is complete. \square

Now, let's consider the perturbed controls of the followers. Suppose the i -th follower \mathcal{A}_i takes the value of $u_i(\cdot)$, while $\mathcal{A}_j(j \neq i)$ still takes $u_j^*(\cdot)$. Then, the centralized state equation for the perturbation of \mathcal{A}_i is

$$\begin{cases} dx_{-i} = \left(A_1 x_{-i} + B_1 u_i + E_1 x_-^{(N)} + b_1 \right) dt \\ \quad + \left(C_1 x_{-i} + D_1 u_i + F_1 x_-^{(N)} + \sigma_1 \right) dW_i \\ \quad + \left(\tilde{C}_1 x_{-i} + \tilde{D}_1 u_i + \tilde{F}_1 x_-^{(N)} + \tilde{\sigma}_1 \right) dW, \\ x_{-i}(0) = \xi, \end{cases} \quad (4.9)$$

where $x_-^{(N)}(\cdot) := \frac{1}{N} \left(x_{-i}(\cdot) + \sum_{j=1, j \neq i}^N x_j(\cdot) \right)$. The centralized state equation for the j -th follower \mathcal{A}_j is the following equation

$$\begin{cases} dx_j = \left(A_1 x_j + B_1 u_j^* + E_1 x_-^{(N)} + b_1 \right) dt \\ \quad + \left(C_1 x_j + D_1 u_j^* + F_1 x_-^{(N)} + \sigma_1 \right) dW_j \\ \quad + \left(\tilde{C}_1 x_j + \tilde{D}_1 u_j^* + \tilde{F}_1 x_-^{(N)} + \tilde{\sigma}_1 \right) dW, \\ x_j(0) = \xi. \end{cases} \quad (4.10)$$

The corresponding decentralized states satisfy

$$\begin{cases} d\bar{x}_{-i} = \left(A_1 \bar{x}_{-i} + B_1 u_i + E_1 z + b_1 \right) dt \\ \quad + \left(C_1 \bar{x}_{-i} + D_1 u_i + F_1 z + \sigma_1 \right) dW_i \\ \quad + \left(\tilde{C}_1 \bar{x}_{-i} + \tilde{D}_1 u_i + \tilde{F}_1 z + \tilde{\sigma}_1 \right) dW, \\ \bar{x}_{-i}(0) = \xi. \end{cases} \quad (4.11)$$

and

$$\left\{ \begin{array}{l} d\bar{x}_j = (A_1\bar{x}_j + B_1u_j^* + E_1z + b_1) dt \\ \quad + (C_1\bar{x}_j + D_1u_j^* + F_1z + \sigma_1) dW_j \\ \quad + (\tilde{C}_1\bar{x}_j + \tilde{D}_1u_j^* + \tilde{F}_1z + \tilde{\sigma}_1) dW, \\ \bar{x}_j(0) = \xi. \end{array} \right. \quad (4.12)$$

respectively. And then, for the perturbation of the i -th follower \mathcal{A}_i , the corresponding centralized state equation of the leader transforms into

$$\left\{ \begin{array}{l} dx_{0,-i} = (A_0x_{0,-i} + B_0u_0 + E_1x_-^{(N)} + b_1) dt \\ \quad + (C_0x_{0,-i} + D_0u_0 + F_1x_-^{(N)} + \sigma_1) dW_0 \\ \quad + (\tilde{C}_0x_{0,-i} + \tilde{D}_0u_0 + \tilde{F}_1x_-^{(N)} + \tilde{\sigma}_1) dW, \\ x_{0,-i}(0) = \xi_0, \end{array} \right. \quad (4.13)$$

together with the decentralized state equation of the leader

$$\left\{ \begin{array}{l} d\bar{x}_{0,-i} = (A_0\bar{x}_{0,-i} + B_0u_0 + E_1z + b_1) dt \\ \quad + (C_0\bar{x}_{0,-i} + D_0u_0 + F_1z + \sigma_1) dW_0 \\ \quad + (\tilde{C}_0\bar{x}_{0,-i} + \tilde{D}_0u_0 + \tilde{F}_1z + \tilde{\sigma}_1) dW, \\ \bar{x}_{0,-i}(0) = \xi_0, \end{array} \right. \quad (4.14)$$

By the definition (4.1) of ε -Stackelberg-Nash equilibria, we need to show

$$\inf_{u_i(\cdot) \in \mathcal{U}_i^{f,d}} \mathcal{J}_i(u_i(\cdot), u_{-i}^*(\cdot)) \geq \mathcal{J}_i(u_i^*(\cdot), u_{-i}^*(\cdot)) - \varepsilon.$$

Therefore, we only need to consider $u_i(\cdot)$ satisfies $\mathcal{J}_i(u_i(\cdot), u_{-i}^*(\cdot)) \leq \mathcal{J}_i(u_i^*(\cdot), u_{-i}^*(\cdot))$. And then,

$$\mathbb{E} \int_0^T R_0 u_i^2(t) dt \leq \mathcal{J}_i(u_i(\cdot), u_{-i}^*(\cdot)) \leq \mathcal{J}_i(u_i^*(\cdot), u_{-i}^*(\cdot)) \leq J_i(u_i^*(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right),$$

i.e.,

$$\mathbb{E} \int_0^T |u_i(t)|^2 dt \leq K.$$

Lemma 4.3.

$$\begin{aligned} \mathbb{E} \left[\sup_{0 \leq t \leq T} |x_-^{(N)}(t) - z(t)|^2 \right] &= O\left(\frac{1}{N}\right), \\ \sup_{1 \leq i \leq N} \mathbb{E} \left[\sup_{0 \leq t \leq T} |x_{-i}(t) - \bar{x}_{-i}(t)|^2 \right] &= O\left(\frac{1}{N}\right), \\ \mathbb{E} \left[\sup_{0 \leq t \leq T} |x_{0,-i}(t) - \bar{x}_{0,-i}(t)|^2 \right] &= O\left(\frac{1}{N}\right). \end{aligned} \quad (4.15)$$

Proof. First, we get

$$\left\{ \begin{aligned} dx_-^{(N)} &= \left[(A_1 + E_1) x_-^{(N)} + \frac{B_1}{N} u_i + \frac{B_1}{N} \sum_{j \neq i} u_j^* + b_1 \right] dt \\ &+ \frac{1}{N} \left(C_1 x_i + D_1 u_i + F_1 x_-^{(N)} + \sigma_1 \right) dW_i \\ &+ \frac{1}{N} \sum_{j \neq i} \left[C_1 x_j + D_1 u_j^* + F_1 x_-^{(N)} + \sigma_1 \right] dW_j \\ &+ \left[\left(\tilde{C}_1 + \tilde{F}_1 \right) x_-^{(N)} + \frac{\tilde{D}_1}{N} u_i + \frac{\tilde{D}_1}{N} \sum_{j \neq i} u_j^* + \tilde{\sigma}_1 \right] dW, \\ x_-^{(N)}(0) &= \xi. \end{aligned} \right. \quad (4.16)$$

Noting (4.5), we have

$$\left\{ \begin{aligned} d \left(x_-^{(N)} - x^{*(N)} \right) &= \left[(A_1 + E_1) \left(x_-^{(N)} - x^{*(N)} \right) + \frac{B_1}{N} (u_i - u_i^*) \right] dt \\ &+ \frac{1}{N} \left[C_1 (x_i - x_i^*) + D_1 (u_i - u_i^*) + F_1 x_-^{(N)} \right] dW_i \\ &+ \frac{1}{N} \sum_{j \neq i} \left[C_1 (x_j - x_j^*) + F_1 \left(x_-^{(N)} - x^{*(N)} \right) \right] dW_j \\ &+ \left[\left(\tilde{C}_1 + \tilde{F}_1 \right) \left(x_-^{(N)} - x^{*(N)} \right) + \frac{\tilde{D}_1}{N} (u_i - u_i^*) \right] dW, \\ \left(x_-^{(N)} - x^{*(N)} \right) (0) &= 0. \end{aligned} \right.$$

Utilizing a similar approach in the proof of Lemma 4.1, we can obtain

$$\begin{aligned} &\mathbb{E} \left[\sup_{0 \leq s \leq t} \left| x_-^{(N)}(s) - x^{*(N)}(s) \right|^2 \right] \\ &\leq K \mathbb{E} \int_0^t \left(\sup_{0 \leq r \leq s} \left| x_-^{(N)}(r) - x^{*(N)}(r) \right|^2 + \frac{1}{N^2} (u_i - u_i^*)^2(s) \right) ds + O \left(\frac{1}{N} \right). \end{aligned}$$

By applying Gronwall's inequality, the first estimate in (4.15) holds.

Noticing Lemma 4.1, we have

$$\begin{aligned} &\mathbb{E} \left[\sup_{0 \leq t \leq T} \left| x_-^{(N)}(t) - z(t) \right|^2 \right] = \mathbb{E} \left[\sup_{0 \leq t \leq T} \left| x_-^{(N)}(t) - x^{*(N)}(t) + x^{*(N)}(t) - z(t) \right|^2 \right] \\ &\leq 2 \mathbb{E} \left[\sup_{0 \leq t \leq T} \left| x_-^{(N)}(t) - x^{*(N)}(t) \right|^2 \right] + 2 \mathbb{E} \left[\sup_{0 \leq t \leq T} \left| x^{*(N)}(t) - z(t) \right|^2 \right] = O \left(\frac{1}{N} \right). \end{aligned}$$

Then, by standard estimates of SDEs, we can obtain the last two estimates in (4.15). The proof is complete. \square

Lemma 4.4.

$$|\mathcal{J}_i(u_i(\cdot), u_{-i}^*(\cdot)) - J_i(u_i(\cdot))| = O\left(\frac{1}{\sqrt{N}}\right). \quad (4.17)$$

Proof. From (2.4) and (3.4), we get

$$\begin{aligned} & |\mathcal{J}_i(u_i(\cdot), u_{-i}^*(\cdot)) - J_i(u_i(\cdot))| \\ &= \frac{1}{2} \mathbb{E} \left\{ \int_0^T \left\{ Q_1 \left[x_{-i} - \left(\lambda x_{0,-i} + (1-\lambda)x_-^{(N)} \right) \right]^2 - Q_1 \left[\bar{x}_i - \left(\lambda \bar{x}_{0,-i} + (1-\lambda)z \right) \right]^2 \right\} dt \right. \\ & \quad \left. + G_1 \left(x_{-i}^2(T) - \bar{x}_i^2(T) \right) \right\}. \end{aligned}$$

Noting Lemma 4.3, we can obtain

$$\begin{aligned} & \frac{1}{2} \mathbb{E} \int_0^T \left\{ Q_1 \left[x_{-i} - \left(\lambda x_{0,-i} + (1-\lambda)x_-^{(N)} \right) \right]^2 - Q_1 \left[\bar{x}_i - \left(\lambda \bar{x}_{0,-i} + (1-\lambda)z \right) \right]^2 \right\} dt \\ &= \frac{1}{2} \mathbb{E} \int_0^T \left\{ Q_1 \left[x_{-i} - \bar{x}_i - \lambda(x_{0,-i} - \bar{x}_{0,-i}) - (1-\lambda)(x_-^{(N)} - z) \right]^2 \right. \\ & \quad \left. + 2 \left[\bar{x}_i - \left(\lambda \bar{x}_{0,-i} + (1-\lambda)z \right) \right] \left[x_{-i} - \bar{x}_i - \lambda(x_{0,-i} - \bar{x}_{0,-i}) - (1-\lambda)(x_-^{(N)} - z) \right] \right\} dt \\ &\leq \frac{1}{2} \mathbb{E} \left\{ \int_0^T K \left(|x_{-i} - \bar{x}_i|^2 + |x_{0,-i} - \bar{x}_{0,-i}|^2 + |x_-^{(N)} - z|^2 \right) dt \right. \\ & \quad \left. + \left(\int_0^T \left[\bar{x}_i - \left(\lambda \bar{x}_{0,-i} + (1-\lambda)z \right) \right]^2 dt \right)^{\frac{1}{2}} \right. \\ & \quad \left. \times \left(\int_0^T \left[x_{-i} - \bar{x}_i - \lambda(x_{0,-i} - \bar{x}_{0,-i}) - (1-\lambda)(x_-^{(N)} - z) \right]^2 dt \right)^{\frac{1}{2}} \right\} \\ &\leq K \mathbb{E} \left[\int_0^T \left(|x_{-i} - \bar{x}_i|^2 + |x_{0,-i} - \bar{x}_{0,-i}|^2 + |x_-^{(N)} - z|^2 \right) dt \right] \\ & \quad + K \mathbb{E} \left[\int_0^T |x_{-i} - \bar{x}_i|^2 dt \right]^{\frac{1}{2}} + K \mathbb{E} \left[\int_0^T |x_{0,-i} - \bar{x}_{0,-i}|^2 dt \right]^{\frac{1}{2}} + K \mathbb{E} \left[\int_0^T |x_-^{(N)} - z|^2 dt \right]^{\frac{1}{2}} \\ &= O\left(\frac{1}{\sqrt{N}}\right). \end{aligned}$$

Similarly, the order of the terminal term is also $O\left(\frac{1}{\sqrt{N}}\right)$, which completes the proof. \square

The following is the proof of first part of Theorem 4.1.

Proof. Applying Lemma 4.2 and Lemma 4.4, we obtain

$$\mathcal{J}_i(u_i^*(\cdot), u_{-i}^*(\cdot)) \leq J_i(u_i^*(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right) \leq J_i(u_i(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right) \leq \mathcal{J}_i(u_i(\cdot), u_{-i}^*(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right).$$

\square

Next, let us consider a perturbed control $u_0(\cdot)$ for the leader \mathcal{A}_0 , the corresponding centralized state equation is

$$\begin{cases} dx_{-0} = \left(A_0 x_{-0} + B_0 u_0 + E_0 x^{*(N)} + b_0 \right) dt \\ \quad + \left(C_0 x_{-0} + D_0 u_0 + F_0 x^{*(N)} + \sigma_0 \right) dW_0 \\ \quad + \left(\tilde{C}_0 x_{-0} + \tilde{D}_0 u_0 + \tilde{F}_0 x^{*(N)} + \tilde{\sigma}_0 \right) dW, \\ x_{-0}(0) = \xi_0. \end{cases} \quad (4.18)$$

And the corresponding decentralized state equation is

$$\begin{cases} d\bar{x}_{-0} = \left(A_0 \bar{x}_{-0} + B_0 u_0 + E_0 z + b_0 \right) dt \\ \quad + \left(C_0 \bar{x}_{-0} + D_0 u_0 + F_0 z + \sigma_0 \right) dW_0 \\ \quad + \left(\tilde{C}_0 \bar{x}_{-0} + \tilde{D}_0 u_0 + \tilde{F}_0 z + \tilde{\sigma}_0 \right) dW, \\ \bar{x}_{-0}(0) = \xi_0. \end{cases} \quad (4.19)$$

By the definition (4.1) of ε -Stackelberg-Nash equilibria, we need to show

$$\inf_{u_0(\cdot) \in \mathcal{U}_0^{l,d}} \mathcal{J}_0(u_0(\cdot)) \geq \mathcal{J}_0(u_0^*(\cdot)) - \varepsilon.$$

Therefore, we only need to consider $u_0(\cdot)$ satisfies $\mathcal{J}_0(u_0(\cdot)) \leq \mathcal{J}_0(u_0^*(\cdot))$. And then,

$$\mathbb{E} \int_0^T R_0 u_0^2(t) dt \leq \mathcal{J}_0(u_0(\cdot)) \leq \mathcal{J}_0(u_0^*(\cdot)) \leq J_0(u_0^*(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right),$$

i.e.,

$$\mathbb{E} \int_0^T |u_0(t)|^2 dt \leq K.$$

Lemma 4.5.

$$\mathbb{E} \left[\sup_{0 \leq t \leq T} |x_{-0}(t) - \bar{x}_{-0}(t)|^2 \right] = O\left(\frac{1}{N}\right). \quad (4.20)$$

Proof. First, we get

$$\begin{cases} d(x_{-0} - \bar{x}_{-0}) = \left[A_0 (x_{-0} - \bar{x}_{-0}) + E_0 (x^{*(N)} - z) \right] dt \\ \quad + \left[C_0 (x_{-0} - \bar{x}_{-0}) + F_0 (x^{*(N)} - z) \right] dW_0 \\ \quad + \left[\tilde{C}_0 (x_{-0} - \bar{x}_{-0}) + \tilde{F}_0 (x^{*(N)} - z) \right] dW, \\ (x_{-0} - \bar{x}_{-0})(0) = 0. \end{cases}$$

Using standard estimate of SDEs and Lemma 4.1, (4.20) holds. \square

Lemma 4.6.

$$|\mathcal{J}_0(u_0(\cdot)) - J_0(u_0(\cdot))| = O\left(\frac{1}{\sqrt{N}}\right). \quad (4.21)$$

Proof. Since

$$\begin{aligned} & |\mathcal{J}_0(u_0(\cdot)) - J_0(u_0(\cdot))| \\ &= \frac{1}{2} \mathbb{E} \left\{ \int_0^T \left[Q_0(x_{-0} - x^{*(N)})^2 - Q_0(\bar{x}_{-0} - z)^2 \right] dt + G_1 [x_{-0}^2(T) - \bar{x}_{-0}^2(T)] \right\}, \end{aligned}$$

using the same method as in the proof of Lemma 4.2 and noticing Lemma 4.1 and Lemma 4.5, we can prove (4.6). \square

The proof of the second part of Theorem 4.1.

Proof. Applying Lemma 4.2 and Lemma 4.6, we obtain

$$\mathcal{J}_0(u_0^*(\cdot)) \leq J_0(u_0^*(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right) \leq J_0(u_0(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right) \leq \mathcal{J}_0(u_0(\cdot)) + O\left(\frac{1}{\sqrt{N}}\right).$$

\square

5 Conclusion

In this paper, we have considered a linear-quadratic mean field Stackelberg stochastic differential game with partial information and common noise. The state equations of the single leader and multiple followers are general. Decentralized strategies are given by the stochastic maximum principle with partial information and optimal filter technique, and the feedback form of decentralized strategies have been obtained by using some high-dimensional Riccati equations. Finally, the decentralized control strategy obtained has been verified as an ε -Stackelberg-Nash equilibrium of the original game (Problem 2.1).

The general solvability of the high-dimensional Riccati equation (3.51) is rather challenging. Problems with partial observation are an interesting but difficult ones. We will consider these topics in our future research.

References

- [1] F. Bagheri and B. Øksendal, A maximum principle for stochastic control with partial information. *Stoch. Anal. Appl.*, 25, 705-717, 2007.
- [2] M. Bardi and F. Priuli, Linear-quadratic N -person and mean-field games with ergodic cost. *SIAM J. Control Optim.*, 52, 3022-3052, 2014.
- [3] A. Bensoussan, X. Feng, and J. Huang, Linear-Quadratic-Gaussian mean-field-game with partial observation and common noise. *Math. Control Relat. Fields*, 11, 23-46, 2021.

- [4] A. Bensoussan, J. Frehse and P. Yam, *Mean Field Games and Mean Field Type Control Theory*. Springer Briefs in Mathematics, Springer, New York, 2013.
- [5] R. Buckdahn, B. Djehiche, J. Li and S. Peng, Mean field backward stochastic differential equations: A limit approach. *Ann. Probab.*, 37, 1524-1565, 2009.
- [6] R. Carmona and F. Delarue, Probabilistic analysis of mean field games. *SIAM J. Control Optim.*, 51, 2705-2734, 2013.
- [7] W. Cong and J. Shi. Direct approach of linear-quadratic Stackelberg mean field games of backward-forward stochastic systems. *arXiv:2401.15835*.
- [8] K. Du, J. Huang and Z. Wu, Linear-quadratic mean-field-game of backward stochastic differential systems. *Math. Control Relat. Fields*, 8, 2018.
- [9] X. Feng and L. Wang, Stackelberg equilibrium with social optima in Linear-Quadratic-Gaussian mean-field system. *Math. Control Relat. Fields*, 14, 769-799, 2024.
- [10] Y. Hu, J. Huang and X. Li, Linear quadratic mean field game with control input constraint. *ESAIM Control Optim. Calc. Var.*, 24, 901-919, 2018.
- [11] Y. Hu, J. Huang and T. Nie, Linear-Quadratic-Gaussian mixed mean-field games with heterogeneous input constraints. *SIAM J. Control Optim.*, 56, 2835-2877 2018.
- [12] J. Huang and M. Huang, Robust mean field Linear-Quadratic-Gaussian games with unknown L^2 -disturbance. *SIAM J. Control Optim.*, 55, 2811-2840, 2017.
- [13] J. Huang and S. Wang, Dynamic optimization of large-population systems with partial information, *J. Optim. Theory Appl.*, 168, 231-245, 2016.
- [14] J. Huang, S. Wang, and Z. Wu, Backward mean-field linear-quadratic-gaussian (LQG) games: Full and partial information, *IEEE Trans. Automat. Control*, 61, 3784-3796, 2016.
- [15] M. Huang, Large-population LQG games involving a major player: the Nash certainty equivalence principle. *SIAM J. Control Optim.*, 48, 3318-3353, 2010.
- [16] M. Huang, P. Caines and R. Malhamé, Large-population cost-coupled LQG problems with nonuniform agents: Individual-mass behavior and decentralized ε -Nash equilibria, *IEEE Trans. Automat. Control*, 52, 1560-1571, 2007.
- [17] M. Huang, R. Malhamé and P. Caines, Large population stochastic dynamic games: closed-loop McKean-Vlasov systems and the Nash certainty equivalence principle. *Commun. Inf. Syst.*, 6, 221-251, 2006.

- [18] P. Huang, G. Wang, S. Wang and H. Xiao, A mean-field game for a forward-backward stochastic system with partial observation and common noise. *IEEE/CAA J. Autom. Sinica*, 11, 746-759, 2024.
- [19] P. Huang, G. Wang, W. Wang and Y. Wang, A linear-quadratic mean-field game of backward stochastic differential equation with partial information and common noise. *Appl. Math. Comput.*, 446, 127899, 2023.
- [20] M. Huang and M. Zhou, Linear quadratic mean field games: Asymptotic solvability and relation to the fixed point approach. *IEEE Trans. Automat. Control*, 65, 1397-1412, 2020.
- [21] J. Lasry and P. Lions, Mean field games. *Jpn. J. Math.*, 2, 229-260, 2007.
- [22] M. Li, T. Nie, S. Wang and K. Yan, Incomplete information linear-quadratic mean-field games and related Riccati equations. *arXiv:2307.01005*.
- [23] M. Li, T. Nie and Z. Wu, Linear-quadratic large-population problem with partial information: Hamiltonian approach and Riccati approach. *SIAM J. Control Optim.*, 61, 2114-2139, 2023.
- [24] X. Li, J. Sun and J. Xiong, Linear quadratic optimal control problems for mean-field backward stochastic differential equations. *Appl. Math. Optim.*, 80, 223-250, 2019.
- [25] J. Ma and J. Yong, *Forward-backward stochastic differential equations and their applications*, Springer-Verlag, New York, 1999.
- [26] D. Majerek, W. Nowak and W. Ziéba, Conditional strong law of large number. *Int. J. Pure Appl. Math.*, 20, 143-156, 2005.
- [27] J. Moon and T. Başar, Linear quadratic risk-sensitive and robust mean field games. *IEEE Trans. Automat. Control*, 62, 1062-1077, 2017.
- [28] J. Moon and T. Başar, Linear quadratic mean field Stackelberg differential games, *Automatica*, 97, 200-213, 2018.
- [29] S. L. Nguyen and M. Huang, Linear-quadratic-Gaussian mixed games with continuum-parametrized minor players. *SIAM J. Control Optim.*, 50, 2907-2937, 2012.
- [30] M. Nourian, P. Caines, R. Malhamé and M. Huang, Mean field LQG control in leader-follower stochastic multi-agent systems: Likelihood ratio based adaptation. *IEEE Trans. Automat. Control*, 57, 2801-2816, 2012.
- [31] K. Si and Z. Wu, Backward-forward linear-quadratic mean-field Stackelberg games. *Adv. Difference Equ.*, 73, 23, 2021.

- [32] J. Shi, G. Wang and J. Xiong, Leader-follower stochastic differential game with asymmetric information and applications. *Automatica*, 63, 60-73, 2016.
- [33] H. von Stackelberg, *The Theory of the Market Economy*. Oxford University Press, London, 1952.
- [34] N. Şen and P. Caines, Mean field game theory with a partially observed major agent, *SIAM J. Control Optim.*, 54, 3174-3224, 2016.
- [35] N. Şen and P. Caines, Mean field games with partial observation, *SIAM J. Control Optim.*, 57, 2064-2091, 2019.
- [36] B. Wang, Leader-follower mean field LQ games: a direct method. *Asian J. Control*, 26, 617-625, 2024.
- [37] G. Wang, Y. Wang and S. Zhang, An asymmetric information mean-field type linear quadratic stochastic Stackelberg differential game with one leader and two followers. *Optimal Control Appl. Methods*, 41, 1034-1051, 2020.
- [38] G. Wang, Z. Wu and J. Xiong, *An Introduction to Optimal Control of FBSDE with Incomplete Information*. Springer Briefs in Mathematics, Springer, Cham, 2018.
- [39] B. Wang and J. Zhang, Social optima in mean field Linear-Quadratic-Gaussian models with Markov jump parameters. *SIAM J. Control Optim.*, 55, 429-456, 2017.
- [40] J. Yong, A leader-follower stochastic linear quadratic differential game. *SIAM J. Control Optim.*, 41, 1015-1041, 2002.
- [41] J. Yong, X. Zhou, *Stochastic Controls: Hamiltonian Systems and HJB Equations*. Springer-Verlag, New York, 1999.